Onon

RV GenSet

Standard Repair Times

HDKBA, HDKBB



Printed in U.S.A. 5–2004 900–0621



Table of Contents

Contents	Page
Foreword	iv
General Information	v
Types of Standard Repair Times Administrative SRT Troubleshooting SRT Repair SRT Standard Repair Combined Times Manual Organization SRT Coding System Step Numbers General How Standard Repair Times are Developed Cummins/Onan SRT Objectives and Philosophy How Times are Developed Productive Repair Time Time Allowances Work Not Included in A SRT Non-Productive Work Service Accessibility Codes "A" Accessibility Rating "B" Accessibility Rating "C" Accessibility Rating "C" Accessibility Rating "D" Accessibility Rating Standard Repair Combined Times (SRCT) How To Use This Manual Company Action	V V V Vi Vii Vii Vii ix ix X X X X X Xi Xi Xi Xi Xi XV
Group 00 – Complete Engine	1
Administrative Time Troubleshoot Genset Engine	2 2 11 11



Contents	Pag
Group 01 – Cylinder Block	1
Camshaft, Valve	1
Camshaft, Fuel	1
Connecting Rod	1
Connecting Rod Bearings	1
Crankshaft	1
Crankshaft Seal, Front	
Crankshaft Seal, Rear	•
Gear Case Cover	
Piston	,
Group 02 - Cylinder Head	2
Cylinder Head Gasket	2
Valve Guides	2
Valves	
Group 03 – Rocker Levers	2
Valves	:
Group 04 – Cam Follower	2
Group 05 – Fuel System	2
Governor Actuator	
Fuel Pump, Electrical	
Pump, Injection	
Group 06 – Injectors	(
Injectors	
Oil Pan and Gasket	
Oil Pump	
Oil Pickup Tube and Strainer	
Oil Filter and Fluid	
Oil Pressure Relief Valve	
Group 08 – Cooling System	;
Thermostat	
Coolant Pump	
Drive Belt, Water Pump	
Group 11 – Exhaust System	4
Exhaust Manifold	



Contents	Page
Group 13 – Electrical Equipment	45
Starter Motor Glow Plugs Battery Charge Regulator	46 46 46
Group 16 – Mounting Adaptations	47
Belt Drive Pulley Coupling Assembly	48 48
Group 17 – Miscellaneous	49
Vibration Isolators	50 50
Group 25 – Generator	51
Main Rotor Main Stator Brushes	52 52 53
Group 26 – Generator Control	55
DC Wire Harness PCB Control Board Circuit Breaker Start / Stop Switch Hourmeter Relay	56 56 56 56 57 57
Index	50

SRT Request Form



Foreword

The Standard Repair Times (SRT) in this manual represent the time required to perform service repairs on Onan Engine and Generator Sets. These times are representative of an average mechanic in a typical dealer or distributorship using the prescribed hand tools, equipment, and all available service tools and equipment required to perform quality repairs and do all necessary testing.

The use of this manual will:

- Encourage uniform terminology throughout the Cummins/Onan organization
- Standardize Repair Order job description write-ups
- Provide shop managers with a guide for establishing flat rate quotations
- Serve as a basis for Onan Corporation, Inc. to establish its warranty labor obligations

Reporting of errors, omissions, and recommendations for improving this publication is encouraged. Send your suggestions or comments to:

Onan Corporation

1400 73rd Avenue NE Minneapolis, MN 55432

Attn: Service Department



General Information

Standard Repair Times (SRT) are lists of work tasks (procedures) and the time required to perform those tasks. The procedures list the work tasks required to be sure an engine or generator set is ready to return to service at the lowest possible cost to the customer. A Standard Repair Time is equitable when the repair described in the procedure can be performed in a period of time less than or equal to the standard by a journeyman mechanic after he/she has performed that repair on the same model, in the same application at least once. Those SRT that a particular mechanic performs more frequently will often require less time than the standard. Conversely, those SRT that a particular mechanic does not frequently perform may require more time than the standard. Several of the procedures may be required to accurately depict all the work actually performed to return a particular engine or generator set to service because the repair of a particular engine or generator set is often unique in light of the complaint, failure model, progressive damage, condition of the parts and customer desires. To allow for differences in the time required to perform a repair because of interference by the application, a Service Accessibility Code Scheme has been created.

Types of Standard Repair Times

There are three types of SRT. Most often at least one of each type is necessary to accurately depict the repair. The three types are:

- Administrative
- Troubleshooting
- Repair

Administrative SRT

Administrative SRT are intended to provide time to move the vehicle engine or generator set to and from the work area, fill out the repair order, record SRT used, etc. It is intended that an administrative SRT be used only once for each repair order. There are two administrative SRT found in this manual in Group 00 – Complete Engine. One of the administrative SRT is to be used when the repair takes place in a shop operated by the repairing location. The other administrative SRT is to be used when the repair takes place away from the shop operated by the repairing location (road repairs). The time for the road repair administrative SRT is greater to allow for loading and unloading tools, equipment, parts, etc. from the service truck.



Troubleshooting SRT

Troubleshooting SRT are found only in Group 00 – Complete Engine. These SRT are intended to be used when diagnosing and analyzing engine, generator set or component failures. Troubleshooting SRT are broken down in to logical numbered steps. The time for each step is cumulative with successive steps, including the time for the appropriate preceding step(s). Some troubleshooting SRT contain time to remove and install components to perform the check(s) listed. Most do not. If a troubleshooting SRT does **NOT** include required component removal and installation, it is intended that the SRT for the removal and installation of that component be in addition to the troubleshooting SRT. Refer to the following example:

Procedure	Procedure	SRT
Number	Description	Hours
00-055	Troubleshoot – Lubricating Oil Consumption Excessive	
	Includes:	
-01	- Check:	0.4
	 Oil consumption report 	
	 For external oil leaks 	
	 For overfilled oil pan 	
	- Oil specifications	
	 For fuel contamination 	
	 Oil change interval 	
	 For engine oil in torque converter 	
-02	Perform checks in Step 01	1.0
	- Check:	
	 Oil temperature 	
	 Air compressor oil consumption 	
	- Turbocharger seal	
	 Crankcase blowby 	

In the above example, the time required to perform the checks in Step 01 is 0.4 hour. If the problem is not located while performing the checks in Step 01, an additional 0.6 hour is allowed to perform the checks in Step 02 for a total of 1.0 hour. The total troubleshooting time appropriate is the time indicated in the column directly in line with the final step required to locate the problem. The step required to locate the problem may or may not be the last step shown in the troubleshooting SRT. Each step contains information as to which steps are included.

Repair SRT

Repair SRT make up the majority of this manual. These are the SRT that cover the actual repair work. The time shown on the same line as the SRT code and title is the total time for that SRT.

Standard Repair Combined Times

Standard Repair Combined Times (SRCT) provide for the combining of the three types of SRT under one code so that, if appropriate, the user can identify the work performed with fewer SRT codes.



Manual Organization

SRT Coding System

Each SRT has a unique code so that SRT data can be computerized. The numbering system used is common to all the SRT manuals for all Onan engines and generator sets. The portion of the system shown in the manual contains three segments:

"Group Number"	"Procedure Number"	"Step Number"
XX	XXX	XX

Group Numbers

Group numbers (the first two digits in the SRT code) are used to identify major engine components. The following list explains the group numbers used in SRT manuals:

Procedure Numbers

The procedure number consists of three digits. The first digit provides guidance as to the category of the repair. The second and third digits, shown as XX in the following list, are sequential numbers or alpha within the category.

Group Number	Contents of Group	Specific	Description of
Group Number	Contents of Group	Repair Number	Category
00	Complete Engine or Generator Set		
0.4		0\/\	Turnilala ala artira a
01	Cylinder Block	0XX	Troubleshooting
02	Cylinder Head	4 V V	ONLY in Group 00
03	Rocker Levers	1XX	Remove and Install
04	Cam Followers/Tappets	2XX	Rebuild
05	Fuel System	3XX	Replace
06	Injectors and Fuel Lines	4XX	Clean and Visually
			Check or Inspect for
07			Reuse
07	Lubricating Oil System	5 \/\/	M 1: (D (D 1/
08	Cooling System	5XX	Machine/Ream/Dowel/
09	Drive Units		Sleeve
10	Intake Air System	2007	Modify/Cut/Lap
11	Exhaust System	6XX	Adjust/Calibrate
12	Air (Compressed) System		_
13	Electrical Equipment	7XX	Test
14	Engine or Generator Set Testing	9	
15	Instruments and Controls		
16	Mounting Adaptations		
17	Miscellaneous	9XX	(SRCT in Group 99)
			General/Miscellaneous
22	Hardware		
25	Generator Components		
26	Generator Control Components		
27	Transfer Switches		
99	SRCT		



Step Numbers

While all SRT codes will contain a Group and Procedure number, only those procedures that are broken down into steps have step numbers. The step numbers are sequential within a SRT.

General

There is an alphabetic index in the back of the manual. Within a particular group the procedures are arranged in alphabetical order by title, thus are not in code numeric order.

There is also a numerical index in which the procedures are arranged in numeric order and not in alphabetical order.

Within a procedure, the user will note that some lines are indented. This indentation is intended to indicate that the sub-tasks are part of the task under which they are indented.

How Standard Repair Times are Developed

Cummins/Onan SRT Objectives and Philosophy

The objective of Cummins/Onan SRT program is to provide credible and equitable labor time standards and procedures to the worldwide Cummins/Onan service network.

A SRT is credible when the procedure accurately depicts the work that **must** be performed to accomplish a quality engine or generator set repair.

A SRT is equitable when it can be performed in a period of time less than or equal to the standard by a journeyman mechanic after he/she has performed that repair at least once.

To establish credible and equitable SRT with sufficient flexibility to account for differences in complaints, failures, progressive damage, customer desires, etc., SRT have been structured using the following considerations:

- What must ALWAYS be done to the engine or generator set to perform the work.
- What MAY have to be done to the engine or generator set parts dependent on their condition.
- What MAY have to be removed to access the engine or generator set.
- How difficult it is for the mechanic to reach the engine or generator set even after interfering application hardware has been removed.

While the most frequent use of SRT information is the Onan Warranty System, it is Onan's intent that the SRT be applicable to repairs conducted for any customer.

As SRT are developed, it is assumed:

- That all the required tools, equipment, and supplies are available in sufficient quantity and in operating condition.
- That required Onan Service Manuals are available to the mechanic are being used.
- That the correct parts are available when the mechanic needs them.



How Times are Developed

SRT are developed from time studies conducted in the field and Onan Technical Service Personnel. Technical Service Representatives create a comprehensive list of all the work elements or tasks required to perform specific repairs. Field studies are analyzed to find these same work elements or tasks and determine the time required for each. The time for work elements or tasks that are not included in the field time studies is determined by conducting free engine or generator set studies or by estimation using similar elements from existing time studies. A time is determined for each element of the procedure. The time for all elements is then totaled to establish the total productive repair time.

Productive Repair Time

Productive Repair Time is described as the actual time involved doing productive work, such as: removing, disassembling, cleaning, inspecting, machining, installing and adjusting parts or components. In addition, the following operations are considered to be productive work for inclusion in a SRT:

- Clock on and off the job or repair order, including shift changes.
- Move vehicle, engine or generator set to and from the work area.
- Move tool box to the work area.
- Obtain tools from tool box, wipe and put away after use.
- Refer to service manuals.
- Obtain, unpack and clean replacement parts as necessary.
- Package and mark parts removed as necessary for warranty or local consumer laws.
- Operate engine or generator set to check for proper operation.
- Clean work area at completion of shift or repair.
- Properly dispose of used engine fluids such as oil and coolant.
- Write summary of work performed at completion of repair or work shift.
- Help from another mechanic (time for one man to complete the task times two).

Time Allowances

After the total productive time is established, an additional allowance of 15 percent is added to cover the following:

- Personal time of 5 percent for:
 - Scheduled rest breaks
 - Personal phone calls
 - Restroom breaks
 - Shift changes
- Supplementary time of 10 percent to cover normal work interruptions:
 - Seized or hard turning fasteners
 - Extra time for extremely dirty equipment
 - Excessive waiting time for replacement parts
 - Brief assistance to other mechanics (less than 5 minutes)
 - Routine maintenance (not repair) of shop equipment
 - Obtain consumable supplies
 - Technical consultation with shop supervision



The following is an example of how the allowances are calculated to establish the SRT for a procedure where the productive time is 208.7 minute (3.48 hr):

Allowance	Allowance	Time
Туре	Percent (%)	(Minutes)
Productive Repair Time	100	208.7
Personal	5	10.4
Supplementary	<u>10</u>	20.9
TOTAL	115	240.0

Published Standard Repair Time = 4.0 hours

Work Not Included in A SRT

For almost every complete repair there will be one SRT that contains most of the work performed. This is sometimes called a base repair. For example, repairing an engine for high oil consumption often requires use of the SRT title Piston and Rings – Remove and Install. This SRT contains most of the time appropriate for the repair, so it is the base repair. There can be work required that is **not** part of this base SRT. This does not mean that the other work is non–productive, rather that other work is **NOT** required EVERY TIME the pistons and rings are removed and installed. More often than not, this other work is covered by another SRT. If the other work is **not** included in the base repair or in another SRT, the work is probably still productive work required for that particular repair.

Non-Productive Work

Analysis of past SRT time studies reveals the following general types of work that were not considered to be productive:

- Waiting on camshaft gears to heat and cool
- Waiting on another mechanic to finish using special tools or shop equipment
- Hunting for misplaced parts
- Repairing shop equipment
- Sorting through capscrews, to find the correct length, that were all thrown together into one basket during disassembly
- Repairing customer supplied components
- Salvaging parts or tools that have been damaged from improper handling or lack of correct tools
- Clearing off tables, parts carts, parts racks etc. left dirty or loaded with parts from previous repairs on other equipment
- Rework caused by installation of incorrect parts or incorrect installation of correct parts
- Fabrication or modification of special tools or equipment because the correct tools or equipment are not available
- Visiting during non-break time
- Conducting business with tool vendors
- Waiting on other mechanics to provide required help



- Waiting on parts clerk to fill orders for other mechanics
- Unnecessary inspection of new parts
- "Hot Setting" valves and injectors when not required
- Repairs to application hardware
- Rework resulting from failure to follow recommended service practices
- Performing work that is **not** part of the repair order or helping another mechanic

Service Accessibility Codes

Service repairs are affected by engine or generator set accessibility. The more difficult the accessibility, the longer it will take to complete the tasks given in the SRT procedure. Accessibility for a particular application is determined by reviewing the application and rating the degree of difficulty for performing the 20 most common repairs. Four codes (A, B, C and D) are used to classify the degree of difficulty for the service accessibility of a specific model or type of equipment. An "A" accessibility code indicates the engine or generator set is easily accessible. A "D" code indicates the application does not make the engine or generator set as easily accessible, thus the highest degree of difficulty relative to SRT standards. A "S" code is included for special or specific repairs not covered in the other four classifications. The "R" code indicates the repair is completed with the component, engine or generator set removed from the application.

"A" Accessibility Rating

- 1. Engine or generator sets mounted in equipment where 90 percent of the work can be performed while standing on the ground, shop floor, or flat work deck.
- 2. Engine or generator set can be accessed without removing any doors or panels.
- 3. Interfering application hardware can all be removed.
- 4. Clearance is sufficient for hands, wrenches, and drain and fill operations, making visual checks and room to stand and work.

"B" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 70 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine can be gained by removing access panels or doors.
- 3. On 80 percent of the operations, interfering application hardware can be removed.
- 4. On 80 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and room to stand and work.



"C" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 50 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine or generator set can be gained by removing the hood, structural members (bolted in) or sheet metal panels.
- 3. On 60 percent of the operations, interfering application hardware can be removed.
- 4. On 60 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and room to stand and work.

"D" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 25 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine or generator set is limited due to interference from permanently mounted structural members, sheet metal or crossmembers.
- On 40 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and limited room to stand and work.

Standard Repair Combined Times (SRCT)

SRCT are the combination of some of the SRT in the manual within a distinctive code. These SRCT are based on field input of SRT that are most frequently used in combination to describe the most common field repairs on this engine.

Use of SRCT can reduce the amount of time required to determine the labor standard for a specific complete engine or generator set repair. The use of SRCT will also reduce the number of codes required when completing a warranty claim or customer invoice.

SRCT are intended to supplement, NOT replace, SRT. One SRCT code can be used instead of several SRT codes.

It is intended that other appropriate SRT can be used to supplement a SRCT as long as the work does not overlap. If there is overlapping work, do **not** use a SRCT.



How To Use This Manual

1. Determine the actual work performed:

Obtain this information from the work description on the repair order.

2. Determine the Accessibility Code:

- Determine the application from the repair order.
- Look in the "Accessibility Code Listing" on page to determine the accessibility code for the application involved in the repair. If the application is not shown, assume the accessibility code is "B".
- Write down the code.

3. Determine applicable SRCT:

- Find the Contents Page for Group 99 Standard Repair Combined Times.
- Compare the titles to the work performed to determine if a SRCT will apply.
- If there is a SRCT that seems to apply, find that SRCT and compare the SRT within the SRCT to the work performed. If you are not sure of the work included in the SRT, read that SRT and compare the procedure listing with the work performed.
- If a SRCT applies to all or part of the work performed, find the column that contains the same accessibility code determined in Step 2 above.
- Move down the column to the line containing the SRCT code and title and pick out the appropriate time.
- If all the work in the SRCT is performed and additional steps were taken, use the SRCT and continue to Step 4 to cover the additional work.
- If there is NOT an appropriate SRCT, move to Step 4.

4. Determine the appropriate repair SRT:

- Use the information from the repair order to identify the parts involved.
- Use the contents page at the front of the manual or the alphabetical index in the back of the manual to determine the appropriate SRT group for the parts and/or work involved.
- Find the contents page for that group.
- Read the contents page for procedure titles that seem to correspond to the work performed.
- Find the SRT within the group.
- Read the SRT procedure listing to determine the work included.



- If the work performed and the work included in the SRT are the same, all or in part, determine and record the time.
- Repeat the steps in this paragraph until you have determined a SRT for all the work performed.

5. Determine the appropriate troubleshooting SRT:

- Read the repair order to determine what troubleshooting work was performed.
- Find the contents page for Group 00.
- Read the contents page for procedure to determine the work included in each step.
- If the work performed and the work included in the troubleshooting SRT are the same, all or in part, determine and record the time of the SRT step. Remember that troubleshooting SRT are cumulative.

6. Determine the appropriate miscellaneous SRT:

- Read the repair order to determine if any application hardware was removed and installed in order to access the engine or generator set.
- Find the contents page for Group 17.
- Read the contents page for procedure titles that seem to correspond to the work performed.
- Find the SRT within the group.
- Read the SRT procedure to determine the work included in the SRT.
- If the work performed and the work included in the SRT are the same, all or in part, determine and record the time.
- If the work required to application hardware is not given in the SRT manual, determine the time for ONLY this work from the repair order. Record the time for possible use as "99–999" or "Non-SRT Time".

7. Determine the appropriate administrative SRT:

- Both of the administrative SRT are shown at the beginning of Group 00.
- Determine the appropriate SRT.
- Record the time.



8. Determine the total appropriate SRT time:

- Check to be sure that there is no duplication of tasks within the SRT procedures selected. If there is work duplicated by some of those selected, use other information contained in the manual to reduce the time of one of the SRT accordingly. If the information is not available, make an estimate.
- Total all the times obtained during performance of Steps 2 through 7.

Standard Repair Times Review Procedure

Onan Corporation makes every effort to be sure the SRT published in this manual are credible and equitable. It will be necessary to review the published times when one or more of the following changes occur:

- Design changes to special service tools or equipment required to perform the repair
- Changes to the repair procedure

A formal SRT review procedure is available for any Cummins/Onan Authorized Repair Location that believes the SRT shown in this manual are incorrect.

To be sure prompt attention and an accurate appraisal is given to your request, the following guidelines must be met:

- 1. Be sure the technician has followed all the procedures and used all the service tools referred to in the appropriate service manuals.
- 2. Be sure a journeyman technician performed the repair, one who has completed the repair a sufficient number of times to become familiar with the procedure.
- 3. Be sure all the SRT, including supplemental SRT, appropriate for the repair are being used.
- 4. Include as much detail as possible about the specific repair.

NOTE: It is **NOT** the intent of this procedure to provide a forum for appealing or disputing the amount of time or the SRT judged appropriate on a particular warranty claim. Communication of this sort **must** follow the processes shown in the Onan Warranty Administration Manual.

- 5. Provide photographs of the installation.
- 6. Provide copies of all repair orders applicable to the SRT involved, the technicians time cards, and any other information related to the repair that will aid in the review process.
- 7. Be sure to provide the correct name of the repairing location, a phone number, and point of contact.



Company Action

Upon receipt of the request for an SRT review, the following action will be taken:

- 1. The person signing the request will be contacted to acknowledge the receipt of the request.
- 2. All the information provided will be analyzed and compared with the history files of the specific operation.
- 3. All information will be analyzed to determine if an error has been made in the procedure, the operations description, or the published repair time.
- 4. If it is determined the published repair time is incorrect, additional studies/analysis will be performed to establish the correct time. The requester will be notified of the results, and the results will be published in the next SRT update.
- 5. If it is determined that the time and procedure is correct, recommendations and assistance will be offered as needed.



Group 00 – Complete Engine

Contents

	Page
Administrative Time	2
Open/Close Repair Order	2
	_
Troubleshoot	2
Engine Will Not Crank	2
Genset Starts But Stops After Switch Releases	2
High/Low AC Output	3
No AC Output Voltage	3
Unstable Voltage	3
Unblanced Generator Output Voltage	3
Engine Oil Leak	4
Fault Code 1 (High Engine Temperature)	4
Fault Code 2 (Low Oil Pressure)	4
Fault Code 4 (Overcrank)	4
Fault Code 12 (Overvoltage)	5
Fault Code 13 (Undervoltage)	5
Fault Code 14 (Overfrequency)	5
Fault Code 15 (Underfrequency)	5
Fault Code 19 (Open/Shorted Governor Actuator)	6
Fault Code 22 (Actuator Overload)	6
Fault Code 23 (Faulty Oil Pressure Sender)	6
Fault Code 24 (Faulty Temperature Sender)	6
Fault Code 27 (Loss of Voltage Sense)	7
Fault Code 29 (High Battery Voltage)	7
Fault Code 32 (Loss of Quad Sense)	7
Fault Code 35 (Control Card EE Checksum)	7
Fault Code 36 (Engine Stopped)	7
Fault Code 37 (Invalid Set Configuration)	8
Fault Code 38 (Field Overload)	
Fault Code 41 (Grounded Rotor)	8
Fault Code 42 (Control Card ROM)	8
Fault Code 43 (Control Card RAM)	9
Fault Code 45 (Loss of Speed Sense)	9
Fault Code 57 (Excessive Fuel Pump Prime Time)	9
Coolant Loss	9
Genset Cranks But Will Not Start	10
Genset Unstable (Hunts)	10
Excess White Smoke at Start-Up (Warm)	10
Excess White Smoke at Start-Up (Cold)	10
Genset	11
Remove And Install	11
nemove and install	11
Engine	11
Rebuild	11
LIGUUIIU	1.1



Sta	ndard Repair Times	Removed From Chassis	,	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
00-901	Administrative Time – Open/Close Repair Order Includes:	0.4	_	_	_	_	-
	Clock on and off the job						
	 Move equipment to and from work area 						
	Clean work area						
	Record the following:						
	 Genset model number 						
	 Genset serial number 						
	 Customer name and address 						
	 Genset date in service 						
	 Hours of operation 						
	 Write repair procedures 						
00-0AA	Troubleshoot - Engine Will Not Crank	_	-	_	_	_	_
	Includes:						
-01	- Check:	_	_	0.3	_	_	_
	 Battery condition 						
	 Battery connections 						
	 Evaluate fault codes 						
-02	 Perform checks in step 01 	_	-	0.5	_	_	_
	Check:						
	 Manual engine rotation 						
	 Wiring connections to and from control, switch, and starter 						
	Start/Stop switch						
	- Starter						
00-0AB	Troubleshoot – Genset Starts But Stops After Switch Releases	_	_	0.7	_	_	_
	Includes:						
	- Check:						
	AC output						
	 Broken or loose wires 						
	 Proper field resistance reading through brushes open to ground 						



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0AB	Troubleshoot – Genset Starts But Stops After Switch Releases	_	_	0.7	_	_	_	
	 Proper quadrature resistance reading open to ground 							
00-0AD	Troubleshoot – High/Low AC Output	_	-	0.5	_	_	_	
	Includes:							
	- Check:							
	Load balance Problem of Load acceptance							
	Broken or loose wires							
	Output lead configurationEvaluate fault codes							
	- Evaluate fault codes							
00-0AG	Troubleshoot - No AC Output Voltage	_	_	0.3	_	_	_	
	Includes:							
	- Check:							
	 Load breaker closed 							
	 Broken or loose wires 							
	 Evaluate fault codes 							
00-0AH	Troubleshoot – Unstable Voltage	_	-	0.3	_	_	_	
	Includes:							
	- Check:							
	 Connected loads 							
	 Broken or loose wires 							
	 Evaluate fault codes 							
00-0AZ	Troubleshoot – Unblanced Generator Output Voltage	_	-	0.5	_	_	_	
	Includes:							
	- Check							
	 Voltage at genset 							
	 Output lead configuration 							
	 Control voltage sensing connections 							
	 Evaluate fault codes 							



Sta	ndard Repair Times	Removed From		0 :		assis	0 1
		Chassis	,	Service	Acces	ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0CM	Troubleshoot – Engine Oil Leak	_	_	0.5	_	_	_
	Includes:						
	 Clean contaminated area 						
	- Check						
	Oil level						
	 Loose hose or drain fittings 						
	 Leaks while running with dye in oil 						
	 Evaluate fault codes 						
00-0CV	Troubleshoot – Fault Code 1 (High Engine Temperature)	_	_	1.0	_	_	_
	Includes:						
	- Check						
	 Coolant level 						
	 Grounded or shorted sender lead 						
	 Coolant temperature inlet/outlet of radiator 						
	 Blocked air flow 						
	 Pressure cap 						
	 Temperature sender grounded 						
00-0CF	Troubleshoot – Fault Code 2 (Low Oil Pressure)	_	-	0.8	_	_	_
	Includes:						
	- Check						
	Oil level						
	 Broken or loose sender lead 						
	Oil pressure						
	 Pressure sender open 						
00-0CG	Troubleshoot – Fault Code 4 (Overcrank)	_	_	0.5	_	_	_
	Includes:						
	Check						
	 Battery voltage 						
	Fuel supply						
	 Governor actuator operation 						
	 Field resistance 						
	 Quadrature resistance 						



Standard Repair Times		Removed From Chassis	0 ' 1 '1'' 0 1					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0BD	Troubleshoot - Fault Code 12 (Overvoltage)	_	-	0.5	_	_	_	
	Includes:							
	- Check							
	Output voltage							
	- Loads							
	 Control sense lead connections 							
	 Grounded or shorted field windings 							
	 Grounded or shorted stator windings 							
00-0BE	Troubleshoot – Fault Code 13 (Undervoltage)	_	_	0.5	_	_	_	
	Includes:							
	- Check							
	Output voltage							
	- Loads							
	 Control sense lead connections 							
	 Grounded or shorted field windings 							
	 Grounded or shorted stator windings 							
00-0BF	Troubleshoot – Fault Code 14 (Overfrequency)	_	-	0.5	_	_	_	
	Includes:							
	- Check							
	 Engine speed 							
	- Loads							
	 Governor actuator operation 							
	Fuel supply							
00-0BG	Troubleshoot – Fault Code 15 (Underfrequency)	_	_	0.5	_	_	_	
	Includes:							
	- Check							
	 Engine speed 							
	- Loads							
	 Governor actuator operation 							
	Fuel supply							
	AC output							



Sta	ndard Repair Times	Removed From Chassis		Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0BJ	Troubleshoot – Fault Code 19 (Open/Shorted Governor Actuator)	_	_	0.5	_	_	_
	Includes:						
	- Check						
	 Battery voltage 						
	 Leads to actuator for open or grounds. 						
	 Actuator resistance 						
	 Connector P1 pins for bent, missing, corrosion 						
00-0BL	Troubleshoot – Fault Code 22 (Actuator Overload)	-	_	1.0	_	_	_
	Includes:						
	- Check						
	– Load						
	Fuel supply						
	 Intake restriction 						
	 Governor actuator operation 						
00-0BM	Troubleshoot – Fault Code 23 (Faulty Oil Pressure Sender)	_	_	0.5	_	_	_
	Includes:						
	- Check						
	Oil level						
	 Broken or loose sender lead 						
	 Sender resistance 						
	 Oil pressure 						
00-0BN	TTroubleshoot – Fault Code 24 (Faulty Temperature Sender)	_	_	0.5	_	_	_
	Includes:						
	- Check						
	 Coolant level 						
	 Shorted or grounded sender lead 						
	 Sender resistance 						
	 Coolant temperature 						



Sta	ndard Repair Times	Removed From		Convios		assis	Codos
		Chassis	•	Service	Acces	Sibility	Codes
	B 1 N 1 1 B 1 1 1	_		_	•	_	<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0BU	Troubleshoot – Fault Code 27 (Loss of Voltage Sense)	_	_	1.0	_	_	_
	Includes:						
	- Check						
	 Broken or loose voltage sense leads 						
	AC output						
	 Field resistance 						
	 Stator resistance 						
00-0BR	Troubleshoot – Fault Code 29 (High Battery Voltage)	_	-	0.3	-	_	_
	Includes:						
	- Check						
	 Battery voltage 						
	 Battery connections 						
	 Battery charge rate 						
00-0VB	Troubleshoot – Fault Code 32 (Loss of Quad Sense)			0.5			
	Includes:						
	- Check						
	 Battery voltage to set 						
	 Battery connection to battery & set 						
	 Stator resistance (opens/shorts/grounds) 						
	 Rotor resistance (opens/shorts/grounds 						
00-0CA	Troubleshoot – Fault Code 35 (Control Card EE Checksum)	_	-	0.3	-	_	_
	Includes:						
	- Check						
	Verify fault						
00-0BW	Troubleshoot – Fault Code 36 (Engine Stopped)	_	_	1.0	_	_	_
	Includes:						
	- Check						
	Fuel supply						
	 Mechanical engine damage 						



Sta	ndard Repair Times	Removed From Chassis	One in Annualitie Onto					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0BW	Troubleshoot – Fault Code 36 (Engine Stopped)	_	-	1.0	_	_	_	
	 Governor actuator operation 							
	AC output							
	 Field resistance 							
	 Stator resistance 							
00-0CH	Troubleshoot – Fault Code 37 (Invalid Set Configuration)	-	-	0.3	-	_	_	
	Includes:							
	- Check							
	 Broken or loose wiring connections 							
00-0BX	Troubleshoot – Fault Code 38 (Field Overload)	_	_	0.5	_	_	_	
	Includes:							
	Check							
	Frequency							
	- Loads							
	Air inlet							
	 Field resistance 							
	 Stator resistance 							
00-0CI	Troubleshoot – Fault Code 41 (Grounded Rotor)	_	_	0.5	_	_	_	
	Includes:							
	Check							
	Fuel supply							
	 Field resistance 							
00-0CB	Troubleshoot – Fault Code 42 (Control Card ROM)	_	-	0.3	_	_	_	
	Includes:							
	- Check							
	Verify fault							



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
00-0CC	Troubleshoot – Fault Code 43 (Control Card RAM)	_	-	0.3	_	_	_		
	Includes:								
	- Check								
	Verify fault								
00-OBY	Troubleshoot – Fault Code 45 (Loss of Speed Sense)	_	_	0.5	_	_	_		
	Includes:								
	- Check								
	 Field resistance for opens/shorts/grounds 								
	 Quad resistance for opens/shorts/grounds 								
	AC output								
00-0CZ	Troubleshoot – Fault Code 57 (Excessive Fuel Pump Prime Time)	_	_	0.3	_	_	_		
	Includes:								
	- Check								
	 Start/Stop switches (local & remote) 								
	 Shorted wiring on set & remote 								
	Fuel supply								
00-010	Troubleshoot - Coolant Loss	_	_	0.8	_	_	_		
	Includes:								
	- Check								
	 Coolant level 								
	 Cracked or leaking hoses 								
	 Loose hose clamps 								
	 Coolant in oil 								
	 Pressure test cooling system (cold) 								
	 Pressure test cooling system (hot) 								
	 Evaluate fault codes 								



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
00-022	Troubleshoot – Genset Cranks But Will Not Start	_	-	0.5	_	_	_		
	Includes:								
	- Check								
	Fuel supply								
	 Fuel from fuel pump 								
	Glowplugs								
	 Governor actuator operation 								
	 Evaluate fault codes 								
00-041	Troubleshoot – Genset Unstable (Hunts)	_	_	0.5	_	_	_		
	Includes:								
	Check								
	Fuel supply								
	 Loose wire connections 								
	 Governor actuator operation 								
	 Evaluate fault codes 								
00–047	Troubleshoot – Excess White Smoke at Start– Up (Warm)	_	-	1.0	_	_	_		
	Includes:								
	Check								
	 Low engine temperature 								
	Air in fuel								
	 Engine compression 								
00-048	Troubleshoot – Excess White Smoke at Start– Up (Cold)	_	_	0.5	_	_	_		
	Includes:								
	- Check								
	Air in fuel								
	Glowplugs								



Sta	ndard Repair Times	Removed From Chassis	,	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-1AA		_	_	2.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Output leads 						
	Fuel lines						
	Exhaust system						
	 Remove and install 						
	Genset						
	 Test run unit 						
00–201	Engine – Rebuild	_	_	8.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator drive belt 						
	 Engine coupling assembly, drive belt 						
	Flywheel						
	Engine assembly						
	Radiator						
	Muffler						
	Coolant hoses						
	 Governor actuator stator 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	- Lifters						
	 Governor actuator base 						
	 Crankshaft pulley 						



Sta	andard Repair Times	Removed From Chassis	,	Service	_	assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00–201	Engine – Rebuild	_	_	8.0	_	_	_
	 Gearcase cover and gasket 						
	 Oil pan and gasket 						
	 Piston and connecting rod 						
	 Rod bearings 						
	 Oil pump drive gear 						
	 Oil pump and gasket 						
	 Rear main seal carrier 						
	Crankshaft						
	 Main bearing carrier and bearings 						
	- Oil seals						
	 Clean and visually inspect 						
	Crankshaft						
	Camshafts						
	Cylinder block						
	 Hone cylinder (as needed) 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	Test run unit						



Group 01 – Cylinder Block

Contents

	Page
Camshaft, Valve	14 14
Camshaft, Fuel	14 14
Connecting Rod	15 15
Connecting Rod Bearings	16 16
Crankshaft Remove And Install	17 17
Crankshaft Seal, Front	18 18
Crankshaft Seal, Rear	18 18
Gear Case Cover	19 19
Piston	19 19



Sta	ndard Repair Times	Removed From Chassis		Service		assis	Codes
		GridSSIS	'		/ / 10000		
	Dragadura Number and Description	D	^	В	С	D	<u>Special</u>
	Procedure Number and Description	R	Α	Б	C	D	S
01-3AE	Camshaft, Valve - Replace	_	_	5.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Exhaust manifold 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	 Coolant pump drive belt 						
	 Coolant pump 						
	Coolant hoses						
	 Governor actuator stator 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	– Lifters						
	 Governor actuator base 						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	 Camshaft stopper 						
	 Camshaft and gear 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	Test run unit						
01-1AC	Camshaft, Fuel - Replace	_	_	4.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	Soundshield (as needed)						



Sta	ndard Repair Times	Removed From Chassis	,	Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01-1AC	Camshaft, Fuel - Replace	_	_	4.0	_	_	_
	 Coolant pump drive belt 						
	 Air inlet duct assembly 						
	 Coolant pump 						
	 Coolant hoses 						
	 Governor actuator stator 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	 Governor actuator base 						
	 Injection pump 						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	 Idler gear 						
	 Camshaft, fuel stopper 						
	 Camshaft assembly 						
	 Test run unit 						
01–1AA	Connecting Rod – Remove And Install	_	_	6.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines (as needed)						
	 Exhaust manifold 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	 Generator drive belt 						
	 Coolant hoses 						
	 Engine coupling assembly, drive belt 						
	Flywheel						
	 Engine assembly 						
	 Fuel injection supply and return lines 						
	 Valve cover and rocker assembly 						



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis sibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01-1AA	Connecting Rod – Remove And Install	_	_	6.0	_	_	_
	 Cylinder head and gasket 						
	 Oil pan and gasket 						
	 Piston and connection rod 						
	Piston rings						
	 Rod bearings 						
	 Clean and visually inspect crankshaft 						
	 Hone cylinder (as needed) 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	 Test run unit 						
01-3AF	Connecting Rod Bearings – Replace	_	_	6.3	_	_	_
	Includes:						
	 Disconnect and Connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	 Exhaust manifold 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	Coolant hoses						
	 Generator drive belt 						
	 Engine coupling assembly, drive belt 						
	Flywheel						
	 Engine assembly 						
	 Fuel injection supply and return lines 						
	 Valve cover and rocker assembly 						
	 Cylinder head and gasket 						
	 Oil pan and gasket 						
	 Piston and connection rod 						
	 Rod bearings 						



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							Special		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
01-3AF	Connecting Rod Bearings – Replace	_	_	6.3	_	_	_		
	 Clean and visually inspect crankshaft 								
	 Hone cylinder (as needed) 								
	 Torque cylinder head 								
	 Adjust valve lash 								
	 Test run unit 								
01–112	Crankshaft – Remove And Install	_	_	7.0	_	_	_		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	 Exhaust manifold 								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	 Air inlet duct assembly 								
	 Generator drive belt 								
	 Engine coupling assembly, drive belt 								
	Flywheel								
	 Engine assembly 								
	 Coolant pump drive belt 								
	 Coolant pump 								
	 Coolant hoses 								
	 Governor actuator stator 								
	 Fuel injection supply and return lines 								
	 Valve cover rocker assembly and pushrods 								
	 Cylinder head and gasket 								
	Lifters								
	 Governor actuator base 								
	 Crankshaft pulley 								
	 Gearcase cover and gasket 								
	 Oil pan and gasket 								
	 Piston and connecting rod 								



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
01–112	Crankshaft – Remove And Install	_	_	7.0	_	_	_	
	 Rod bearings 							
	 Oil pump drive gear 							
	 Oil pump and gasket 							
	 Rear main seal carrier 							
	Crankshaft							
	 Main bearing carrier and bearings 							
	– Oil seals							
	 Clean and visually inspect crankshaft 							
	 Hone cylinder (as needed) 							
	 Torque cylinder head 							
	Adjust valve lash							
	 Test run unit 							
01–304	Crankshaft Seal, Front – Replace	_	_	1.5	_	_	_	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Remove and install							
	 Soundshield (as needed) 							
	 Air inlet duct assembly 							
	 Coolant pump drive belt 							
	Crankshaft pulley							
	– Oil seal							
	 Crankshaft collet and o-ring 							
	Test run unit							
01–308	Crankshaft Seal, Rear – Replace	_	_	2.0	_	_	_	
01-306	Includes:			2.0				
	Disconnect and connect							
	Battery cables							
	Engine wiring harness (as needed)							
	Remove and install							
	 Soundshield (as needed) 							



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
01–308	Crankshaft Seal, Rear – Replace	_	-	2.0	_	_	_	
	Generator drive belt							
	 Engine coupling assembly, drive belt 							
	– Flywheel							
	Bearing case cover							
	- Oil seal							
	 Visually inspect for oil leaks 							
	 Test run unit 							
01–121	Gear Case Cover – Remove And Install	_	_	3.0	_	_	_	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Air inlet duct assembly 							
	 Coolant pump drive belt 							
	 Coolant pump 							
	 Coolant hoses 							
	 Governor actuator stator 							
	 Governor actuator base 							
	 Crankshaft pulley 							
	 Gearcase cover and gasket 							
	 Test run unit 							
01–140	Piston – Remove And Install	_	_	5.5	_	_	_	
	Includes:							
	 Disconnect and connect 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust manifold 							
	 Drain and refill engine fluids 							
	 Remove and install 							



ndard Repair Times	Removed From Chassis				Codes	
						<u>Special</u>
Procedure Number and Description	R	Α	В	С	D	S
(continued from previous page)						
Piston – Remove And Install	_	_	5.5	_	_	_
 Soundshield (as needed) 						
 Air inlet duct assembly 						
 Generator drive belt 						
 Engine coupling assembly, drive belt 						
Flywheel						
Coolant hoses						
 Engine assembly 						
 Fuel injection supply and return lines 						
 Valve cover and rocker assembly 						
 Cylinder head and gasket 						
 Oil pan and gasket 						
 Piston and connecting rod 						
Piston rings						
 Clean and visually inspect crankshaft 						
 Hone cylinder (as needed) 						
 Torque cylinder head 						
 Adjust valve lash 						
 Test run unit 						
	Procedure Number and Description (continued from previous page) Piston - Remove And Install - Soundshield (as needed) - Air inlet duct assembly - Generator drive belt - Engine coupling assembly, drive belt - Flywheel - Coolant hoses - Engine assembly - Fuel injection supply and return lines - Valve cover and rocker assembly - Cylinder head and gasket - Oil pan and gasket - Piston and connecting rod - Piston rings - Clean and visually inspect crankshaft - Hone cylinder (as needed) - Torque cylinder head - Adjust valve lash	Procedure Number and Description (continued from previous page) Piston - Remove And Install - Soundshield (as needed) - Air inlet duct assembly - Generator drive belt - Engine coupling assembly, drive belt - Flywheel - Coolant hoses - Engine assembly - Fuel injection supply and return lines - Valve cover and rocker assembly - Cylinder head and gasket - Oil pan and gasket - Piston and connecting rod - Piston rings - Clean and visually inspect crankshaft - Hone cylinder (as needed) - Torque cylinder head - Adjust valve lash	Procedure Number and Description (continued from previous page) Piston – Remove And Install - Soundshield (as needed) - Air inlet duct assembly - Generator drive belt - Engine coupling assembly, drive belt - Flywheel - Coolant hoses - Engine assembly - Fuel injection supply and return lines - Valve cover and rocker assembly - Cylinder head and gasket - Oil pan and gasket - Piston and connecting rod - Piston rings - Clean and visually inspect crankshaft - Hone cylinder (as needed) - Torque cylinder head - Adjust valve lash	Procedure Number and Description R A B (continued from previous page) Piston – Remove And Install Soundshield (as needed) Air inlet duct assembly Generator drive belt Engine coupling assembly, drive belt Flywheel Coolant hoses Engine assembly Fuel injection supply and return lines Valve cover and rocker assembly Cylinder head and gasket Oil pan and gasket Piston and connecting rod Piston rings Clean and visually inspect crankshaft Hone cylinder (as needed) Torque cylinder head Adjust valve lash	Procedure Number and Description R A B C (continued from previous page) Piston – Remove And Install — Soundshield (as needed) — Air inlet duct assembly — Generator drive belt — Engine coupling assembly, drive belt — Flywheel — Coolant hoses — Engine assembly — Fuel injection supply and return lines — Valve cover and rocker assembly — Cylinder head and gasket — Piston and connecting rod — Piston rings — Clean and visually inspect crankshaft — Hone cylinder (as needed) — Torque cylinder head — Adjust valve lash	Procedure Number and Description R A B C D (continued from previous page) Piston – Remove And Install Soundshield (as needed) Air inlet duct assembly Generator drive belt Engine coupling assembly, drive belt Flywheel Coolant hoses Engine assembly Fuel injection supply and return lines Valve cover and rocker assembly Cylinder head and gasket Piston and connecting rod Piston rings Clean and visually inspect crankshaft Hone cylinder (as needed) Torque cylinder head Adjust valve lash



Group 02 – Cylinder Head

	Page
Cylinder Head Gasket	22
Replace	22
Valve Guides	22
Replace	22
Valves	
Replace	23



Standard Repair Times		Removed From Chassis		Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
02-3AA	Cylinder Head Gasket – Replace	-	-	3.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Exhaust manifold 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	Coolant pump						
	Coolant hoses						
	 Governor actuator stator 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	Clean carbon off						
	 Cylinder head 						
	Tops of pistons						
	- Around valve ports						
	- Torque cylinder head						
	Adjust valve lash						
	Test run unit						
02-302	Valve Guides – Replace	-	-	4.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Exhaust manifold						
	 Drain and refill engine fluids 						
	Remove and install						
	Soundshield (as needed)						
	Air inlet duct assembly						



Standard Repair Times		Removed From Chassis						
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
02-302	Valve Guides – Replace	-	-	4.0	-	-	-	
	 Coolant pump drive belt 							
	 Coolant pump 							
	 Coolant hoses 							
	 Governor actuator stator 							
	 Fuel injection supply and return lines 							
	 Valve cover rocker assembly and pushrods 							
	 Cylinder head and gasket (as needed) 							
	 Remove and install from head 							
	- Caps							
	 Spring collet, retainer, and spring 							
	Stem seal							
	Valve							
	Valve guides							
	 Clean carbon off 							
	 Cylinder head 							
	Tops of piston							
	 Around valve ports 							
	 Lap valves of valve seats 							
	 Torque cylinder head 							
	 Adjust valve lash 							
	 Test run unit 							
02-513	Valves – Replace	-	-	3.8	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	 Exhaust manifold 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Air inlet duct assembly 							
	 Coolant pump drive belt 							



Standard Repair Times		Removed From Chassis		Service	_	assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
02–513	Valves - Replace	-	-	3.8	-	-	-
	 Coolant pump 						
	 Coolant hoses 						
	 Governor actuator stator 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket (as needed) 						
	 Remove and install from head 						
	- Caps						
	 Spring collet, retainer, and spring 						
	Stem seal						
	- Valve						
	 Clean carbon off 						
	 Cylinder head 						
	Tops of piston						
	 Around valve ports 						
	 Lap valves of valve seats 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	 Test run unit 						
				1			



Group 03 – Rocker Levers

	Pa	ge
Valves	4	26
Adjust		26



Sta	Standard Repair Times		In-Chassis Service Accessibility Codes			Codes	
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
03-603	Valves – Adjust	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Glowplugs						
	Valve cover						
	 Adjust valve lash 						
	 Test run unit 						



Group 04 – Cam Follower

	Page
Valve Tappets	28
Remove And Install	



Standard Nepali Tillies		Removed From Chassis		Service		nassis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
04–118	Valve Tappets – Remove And Install	-	-	3.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Exhaust manifold 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	 Coolant pump 						
	 Coolant hoses 						
	 Governor actuator stator 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket (as needed) 						
	Tappets						
	 Clean carbon off 						
	 Cylinder head 						
	Tops of pistons						
	 Around valve ports 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	 Test run unit 						



Group 05 – Fuel System

	Page
Governor Actuator	30
Replace	30
Fuel Pump, Electrical	30
Replace	30
Pump, Injection	30
Replace	30



Standard Repair Times		Removed From Chassis	rom On the American lattice One					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
05-1AB	Governor Actuator – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Remove and install - Soundshield (as needed) - Actuator cover - Shaft spring and bearing carrier assembly - Actuator stator - Actuator rotor - Actuator base	-	-	1.8	-	-	-	
05-1AC	 Reset high engine idle and stop screws Test run unit Fuel Pump, Electrical – Replace Includes: Disconnect and connect Battery cables Engine wiring harness (as needed) Remove and install Soundshield (as needed) Fuel lines (as needed) Radiator Fuel pump shield Starter Fuel pump 	-	-	1.5	-	-	-	
05–102	Pump, Injection – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed)	-	-	2.0	-	-	-	



Sta	ndard Repair Times	Removed From Chassis			Codes		
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
05–102	Pump, Injection - Replace	-	-	2.0	-	-	-
	 Remove and install 						
	 Soundshield (as needed) 						
	 Governor actuator cover & stator 						
	 Intake air resonator 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	 Fuel injection pump 						
	 Test run unit 						





Group 06 – Injectors

	raye
Injectors	34
Replace	34



Sta	ndard Repair Times	Removed From Chassis	;	Service		nassis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
06–149	Injectors – Replace	-	-	1.8	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Governor actuator cover & stator 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	Injectors						
	 Test run unit 						



Group 07 – Lubricating Oil System

	Page
Oil Pan and Gasket	36
Replace	36
Oil Pump	36
Replace	36
Oil Pickup Tube and Strainer	37
Replace	37
Oil Filter and Fluid	
Replace	37
Oil Pressure Relief Valve	
Inspect and Replace	38



Sta	andard Repair Times Removed From Chassis			In-Chassis Service Accessibility Codes				
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
07–109	Oil Pan and Gasket – Replace	-	-	4.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust manifold & muffler 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Air inlet duct assembly 							
	 Generator drive belt 							
	 Coolant hoses 							
	 Engine coupling assembly, drive belt 							
	– Flywheel							
	Engine assembly							
	Oil pan and gasket							
	Test run unit							
07–113	Oil Pump - Replace	-	-	4.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Air inlet duct assembly 							
	 Coolant pump drive belt 							
	Coolant pumps							
	Coolant hoses							
	 Governor actuator stator 							
	 Governor actuator base 							
	 Crankshaft pulley 							



Sta	Removed From Chassis	From					
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
07–113	Oil Pump – Replace	-	-	4.0	-	-	-
	 Gearcase cover and gasket 						
	 Oil pump drive gear 						
	 Oil pump and gasket 						
	 Test run unit 						
07–114	Oil Pickup Tube and Strainer – Replace Includes:	-	-	4.2	-	-	-
	 Disconnect and connect 						
	- Battery cables						
	Engine wiring harness (as needed)						
	- Fuel lines						
	Exhaust manifold						
	Drain and refill engine fluids						
	Remove and install						
	- Soundshield (as needed)						
	- Air inlet duct assembly						
	- Generator drive belt						
	Engine coupling assembly, drive belt						
	- Flywheel						
	Engine assemblyOil pan and gasket						
	Oil pickup tube and strainerTest run unit						
	- Test run unit						
07–301	Oil Filter and Fluid – Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	Oil filter						
	 Test run unit 						



Standard Repair Times		Removed From Chassis	(Service	_	assis sibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
07–410	Oil Pressure Relief Valve – Inspect and Replace	-	-	0.8	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	Oil filter						
	 Valve assembly 						
	 Clean and visually inspect or replace 						
	 Bore, spring, ball, and seat 						
	- Test run unit						



Group 08 – Cooling System

	Page
Thermostat	40
Replace	40
Coolant Pump	40
Replace / Rebuild	40
Drive Belt, Water Pump	41
Adjust / Replace	41



Sta	Standard Repair Times		,	Service		assis sibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
08–104	Thermostat – Replace			0.8		_	
00-104	Includes:			0.0		_	_
	Disconnect and connect						
	Battery cables						
	Engine wiring harness (as needed)						
	Drain and refill engine fluids						
	Remove and install						
	Soundshield (as needed)						
	Coolant hoses						
	Thermostat cover and gasket						
	- Thermostat						
	Test run unit						
08–209	Coolant Pump – Replace / Rebuild	-	-	1.8	-	-	-
	Includes:						
	 Disconnect and connect 						
	Battery cables						
	Drain and refill engine fluids						
	- Remove and install						
	 Soundshield (as needed) 						
	Pump drive belt Coclert nump						
	Coolant pump						
	- Impeller						
	- Seal assembly						
	- Shaft assembly						
	- Pulley						
	- Pump gasket						
	Inspect pump housingTest run unit						
	- Test full utilit						



Sta	Standard Repair Times		In-Chassis Service Accessibility Codes				
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
08–302	Drive Belt, Water Pump - Adjust / Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Remove and install 						
	 Soundshield (as needed) 						
	- Pulley						
	 Pump drive belt 						
	 Test run unit 						





Group 11 – Exhaust System

	Page
Exhaust Manifold	44
Replace	44



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes			Codes	
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
11–3AA	Exhaust Manifold – Replace	-	-	2.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Exhaust manifold and gasket 						
	 Test run unit 						



Group 13 – Electrical Equipment

	Page
Starter Motor	. 46
Replace	. 46
Glow Plugs	. 46
Replace	. 46
Battery Charge Regulator	. 46
Replace	. 46



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes			Codes	
	Procedure Number and Description	R	Α	В	С	D	<u>Special</u> S
	<u>'</u>						
13–104	Starter Motor - Replace	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Starter						
	Test run unit						
13–114	Glow Plugs – Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Glowplugs						
	 Test run unit 						
13–3AD	Battery Charge Regulator – Replace	-	_	0.8	-	_	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Glowplug relay and base 						
	 Regulator assembly 						
	 Heat sink cooling fins 						
	 Test run unit 						



Group 16 – Mounting Adaptations

	Page
Belt Drive Pulley Coupling Assembly	
Flywheel	



Standard Repair Times		Removed From Chassis	1 11-01103515					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
16-1AB	Belt Drive Pulley Coupling Assembly – Inspect and Replace	-	-	2.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Drive belt							
	Drive pulley							
	 Drive pulley bushing 							
	 Hub assembly 							
	Flex coupling							
	 Test run unit 							
16–103	Flywheel – Replace	-	-	1.5	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Drive belt							
	Drive pulley							
	 Hub assembly 							
	Flywheel							
	 Test run unit 							



Group 17 – Miscellaneous

	Page
Vibration Isolators	
Replace	50
Sound Shield	
Replace	50



Standard Repair Times Removed From Chassis Servi		In-Chassis Service Accessibility Codes					
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
17–1AB	Vibration Isolators – Replace	_	_	2.3	-	_	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	Drip tray						
	 Vibration isolator 						
	 Test run unit 						
17-1AC	Sound Shield - Replace	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield 						
	 Test run unit 						



Group 25 – Generator

	Page
Main Rotor	52
Replace	52
Main Stator	52
Replace	52
Brushes	53
Replace	53



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Co		Codes		
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
25-1AA	Main Rotor – Replace	-	-	3.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Drive belt						
	 Generator pulley 						
	 Intake resonator 						
	 Air inlet duct assembly 						
	 Brush block assembly 						
	 Cooling fan 						
	 End bell / bearing carrier 						
	Main stator						
	 Main rotor assembly 						
	Check brush alignment						
	Test run unit						
25-1AB	Main Stator - Replace	-	-	2.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Air inlet duct assembly 						
	 Intake resonator 						
	 Brush block assembly 						
	 Cooling fan 						
	 End bell / bearing carrier 						
	Main stator						
	 Check brush alignment 						
	Test run unit						
	– Test run unit						



Sta	ndard Repair Times	Removed From Chassis			/ Codes		
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
25-3AB	Brushes - Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	Access door						
	 Brush block assembly 						
	 Check brush alignment 						
	 Test run unit 						





Group 26 – Generator Control

	Page
DC Wire Harness	56
Replace	. 56
PCB Control Board	
Replace	. 56
Circuit Breaker	56
Replace	. 56
Start / Stop Switch	56
Replace	
Hourmeter	57
Replace	. 57
Relay	57
Replace	. 57



Standard Repair Times		Removed From Chassis	0 ' 4 '' ''' 0 '				
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
26-1AB	DC Wire Harness – Replace	-	-	2.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Electrical connectors 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Electrical wiring 						
	 Intake resonator & control 						
	 Adjust belt tension 						
	 Test run unit 						
26-3AB	PCB Control Board - Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Access panel 						
	Control						
	Test run unit						
26-3AE	Circuit Breaker - Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Remove and install 						
	Access panel						
	Circuit breaker						
	Test run unit						
26-3AJ	Start / Stop Switch - Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						



Standard Repair Times		Removed From Chassis Service Accessibility Cod			Codes		
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
26-3AJ	Start / Stop Switch - Replace	-	-	0.3	-	-	-
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	Start / stop switch						
	 Test run unit 						
26-3AK	Hourmeter – Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	Hourmeter						
	 Test run unit 						
26-3AL	Relay – Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Remove and install 						
	 Soundshield (as needed) 						
	- Relay						
	Test run unit						





Α

Administrative Time, Open/Close Repair Order (Shop), 2

В

Battery Charge Regulator, Replace, 46
Belt Drive Pulley Coupling Assembly, Inspect and Replace, 48
Brushes, Replace, 53

C

Camshaft, Fuel, Replace, 14
Camshaft, Valve, Replace, 14
Circuit Breaker, Replace, 56
Connecting Rod, Remove And Install, 15
Connecting Rod Bearings, Replace, 16
Coolant Pump, Replace / Rebuild, 40
Crankshaft, Remove And Install, 17
Crankshaft Seal, Front, Replace, 18
Crankshaft Seal, Rear, Replace, 18
Cylinder Head Gasket, Replace, 22

D

DC Wire Harness, Replace, 56
Drive Belt, Water Pump, Adjust / Replace, 41

E

Engine, Rebuild, 11 Exhaust Manifold, Replace, 44

F

Flywheel, Replace, 48 Fuel Pump, Electrical, Replace, 30

G

Gear Case Cover, Remove and Install, 19 Genset, Remove and Install, 11 Glow Plugs, Replace, 46 Governor Actuator, Replace, 30

H

Hourmeter, Replace, 57

I

Injectors, Replace, 34

M

Main Rotor, Replace, 52 Main Stator, Replace, 52

O

Oil Filter and Fluid, Replace, 37
Oil Pan and Gasket, Replace, 36
Oil Pickup Tube and Strainer, Replace, 37
Oil Pressure Relief Valve, Inspect and Replace, 38
Oil Pump, Replace, 36

P

PCB Control Board, Replace, 56 Piston, Remove and Install, 19 Pump, Injection, Replace, 30

R

Relay, Replace, 57



S

Sound Shield, Replace, 50 Start / Stop Switch, Replace, 56 Starter Motor, Replace, 46

T

Thermostat, Replace, 40

Troubleshoot

Coolant Loss, 9

Engine Oil Leak, 4

Engine Will Not Crank, 2

Excess White Smoke at Start-Up (Cold), 10

Excess White Smoke at Start-Up (Warm), 10

Fault Code 1 (High Engine Temperature), 4

Fault Code 12 (Overvoltage), 5

Fault Code 13 (Undervoltage), 5

Fault Code 14 (Overfrequency), 5

Fault Code 15 (Underfrequency), 5

Fault Code 19 (Open/Shorte Governor Actuator), 6

Fault Code 2 (Low Oil Pressure), 4

Fault Code 22 (Actuator Overload), 6

Fault Code 23 (Faulty Oil Pressure Sender), 6

Fault Code 24 (Faulty Temperature Sender), 6

Fault Code 27 (Loss of Voltage Sense), 7

Fault Code 29 (High Battery Voltage), 7

Fault Code 32 (Loss of Quaf Sense), 7

Fault Code 35 (Control Card EE Checksum), 7

Fault Code 36 (Engine Stopped), 7

Fault Code 37 (Invalid Set Configuration), 8

Fault Code 38 (Field Overflow), 8

Fault Code 4 (Overcrank), 4

Fault Code 41 (Grounded Rotor), 8

Fault Code 42 (Control Card ROM), 8

Fault Code 43 (Control Card RAM), 9

Fault Code 45 (Loss of Speed Sense), 9

Fault Code 57 (Excessive Fuel Pump Prime Time), 9

inne), 9

Genset Cranks But Will Not Start, 10

Genset Starts But Stops After Switch Releases,

Genset Unstable (Hunts), 10

High/Low AC Output, 3

No AC Output Voltage, 3

Unblanced Generator Output Voltage, 3

Unstable Voltage, 3



Valve Guides, Replace, 22

Valve Tappets, Remove and Install, 28

Valves

Adjust, 26

Replace, 23

Vibration Isolators, Replace, 50



Request for SRT review

Distributor/Dea	aler Data				
Distributor/Dea	aler			Phone No.	
Address					
City		St	tate	Zip Code	
Country					
My experience	has indicated th	ne following rep	air procedures	require mo	e time:
Procedure Dat	а				
SRT Number	Procedure I	Discription	Published	time Hrs.	Suggested time Hrs
			To	tal Hours	
Generator Set	Model				
Transfer Switch	h Model				
Repair Date					
Technician Na	me				
		_			
Describe how	repair was perfo	ormed:			
Signature			Title		
Mada A	0				
Mail to: Ona Serv 1400 Mini	n Corporation vice Department) 73rd Avenue N neapolis, MN 554	E 132			







Cummins Power Generation 1400 73rd Avenue N.E. Minneapolis, MN 55432 763-574-5000 Fax: 763-528-7229

