

MARINE

Standard Repair Times

MDKAV, MDKAW, MDKAZ, MDKBG, MDKBK, MDKBL, MDKBM, and MDKBN

	-
	
_	
	
-	
	
	
	
	_
•	
•	-
•	



Table of Contents

Contents	Page
Foreword	v
General Information	vi
Types of Standard Repair Times	vi
Administrative SRTs	vi
Troubleshooting SRTs	vii
Repair SRTs	vii
Standard Repair Combined Times	vii
Manual Organization	viii
SRT Coding System	viii
Step Numbers	ix
General	ix
How Standard Repair Times are Developed	ix
Cummins/Onan SRT Objectives and Philosophy	ix
How Times are Developed	Х
Productive Repair Time	Х
Time Allowances	X
Work Not Included in A SRT	xi
Non-Productive Work	xi
Service Accessibility Codes	xii
"A" Accessibility Rating	xii
"B" Accessibility Rating	xii
"C" Accessibility Rating	xiii
"D" Accessibility Rating	xiii
Standard Repair Combined Times (SRCTs)	xiii
How To Use This Manual	xiv
Company Action	xvii
Group 00 – Complete Engine or Generator Set	1
	0
Administrative Time Troubleshoot	3
	3
Troubleshoot	8 18
Genset (Relaw Dock)	18
Genset (Below Deck)	19
· · · · · · · · · · · · · · · · · · ·	20
Genset Engine Assembly	20



Contents	Page
Group 01 – Cylinder Block	23
Camshaft, Valve	24
Camshaft, Fuel	24
Connecting Rod	25
Connecting Rod Bearings	26
Crankshaft	27
Gear, Crankshaft	28
Gear Case Cover	28
Piston	29
Crankshaft Seal, Front	30
Crankshaft Seal, Rear	30
Group 02 – Cylinder Head	33
Cylinder Head Gasket	34
Valve Guides	34
Valves	36
Group 03 – Rocker Levers	37
Valves	38
Breather	38
Group 04 – Cam Followers/Tappets	39
Valve Tappets	40
Group 05 – Fuel System	41
Governor Actuator	42
Fuel Pump, Electrical	42
Pump, Injection	43
Group 06 – Injectors and Fuel Lines	45
• •	
Injectors	46
Group 07 – Lubricating Oil System	47
Oil Pan and Gasket	48
Oil Pump	48
Oil Pickup Tube and Strainer	49
Oil Filter and Fluid	49
Oil Dragging Dalief Value	EΩ



Contents	Page
Group 08 – Cooling System	51
Thermostat Heat Exchanger Water Pipe Belt Guard Raw Water Pump	52 52 53 53 53 54
Coolant Pump Drive Belt, Water Pump	55 55
Group 10 – Intake Air System	57
Air Intake Silencer	58 58
Group 11 – Exhaust System	59
Exhaust Manifold Exhaust Mixer	60 60
Group 13 – Electrical Equipment	61
Alternator Starter Motor Glow Plugs	62 62 63
Group 16 – Mounting Adaptations	65
Flywheel Flywheel Housing	66 66
Group 17 - Miscellaneous	67
Exhaust Tube Vibration Isolators Sound Shield Muffler, Aqualift	68 68 69
Group 21 – Generator Equipment	71
Main Circuit Breaker (AC) Oil Pressure Sender Gauge Temperature Sender	72 72 73 73



Contents	Page
Group 25 – Generator	75
Main Rotor	76
Main Stator	76
Exciter Rotor	77
Exciter Stator	77
Generator Bearing	78
Rotating Diode Assemblies	78
Group 26 – Generator Control Components	79
DC Wire Harness	80
AC Control Box	80
Digital Display	80
PCB Control Board	81
Circuit Breaker (DC)	81
Start / Stop Switch	82
Hourmeter	82
Relay	83
PCB Network Interface Module (NIM)	83
Index	85

SRT Request Form



Foreword

The Standard Repair Times (SRTs) in this manual represent the time required to perform service repairs on Onan Engine and Generator Sets. These times are representative of an average mechanic in a typical dealer or distributorship using the prescribed hand tools, equipment, and all available service tools and equipment required to perform quality repairs and do all necessary testing.

The use of this manual will:

- Encourage uniform terminology throughout the Cummins/Onan organization
- Standardize Repair Order job description write-ups
- Provide shop managers with a guide for establishing flat rate quotations
- Serve as a basis for Onan Corporation, Inc. to establish its warranty labor obligations

Reporting of errors, omissions, and recommendations for improving this publication is encouraged. Send your suggestions or comments to:

Onan Corporation

1400 73rd Avenue NE Minneapolis, MN 55432

Attn: Service Department



General Information

Standard Repair Times (SRTs) are lists of work tasks (procedures) and the time required to perform those tasks. The procedures list the work tasks required to be sure an engine or generator set is ready to return to service at the lowest possible cost to the customer. A Standard Repair Time is equitable when the repair described in the procedure can be performed in a period of time less than or equal to the standard by a journeyman mechanic after he/she has performed that repair on the same model, in the same application at least once. Those SRTs that a particular mechanic performs more frequently will often require less time than the standard. Conversely, those SRTs that a particular mechanic does not frequently perform may require more time than the standard. Several of the procedures may be required to accurately depict all the work actually performed to return a particular engine or generator set to service because the repair of a particular engine or generator set is often unique in light of the complaint, failure model, progressive damage, condition of the parts and customer desires. To allow for differences in the time required to perform a repair because of interference by the application, a Service Accessibility Code Scheme has been created.

Types of Standard Repair Times

There are three types of SRTs. Most often at least one of each type is necessary to accurately depict the repair. The three types are:

- Administrative
- Troubleshooting
- Repair

Administrative SRTs

Administrative SRTs are intended to provide time to move the vehicle engine or generator set to and from the work area, fill out the repair order, record SRT used, etc. It is intended that an administrative SRT be used only once for each repair order. There are two administrative SRTs found in this manual in Group 00 – Complete Engine. One administrative SRT is to be used when the repair takes place in a shop operated by the repairing location. The other administrative SRT is to be used when the repair takes place away from the shop operated by the repairing location (road repairs). The time for the road repair administrative SRT is greater to allow for loading and unloading tools, equipment, parts, etc. from the service truck.



Troubleshooting SRTs

Troubleshooting SRTs are found only in Group 00 – Complete Engine. These SRTs are intended to be used when diagnosing and analyzing engine, generator set or component failures. Troubleshooting SRTs are broken down into logical numbered steps. The time for each step is cumulative with successive steps, including the time for the appropriate preceding step(s). Some troubleshooting SRTs contain time to remove and install components to perform the check(s) listed. Most do not. If a troubleshooting SRT does **NOT** include required component removal and installation, it is intended that the SRT for the removal and installation of that component be in addition to the troubleshooting SRT. Refer to the following example:

Procedure Number 00-055	Procedure Description Troubleshoot – Lubricating Oil Consumption Excessive Includes:	SRT Hours
-01	- Check:	0.4
01	- Oil consumption report - For external oil leaks	0.4
	- For overfilled oil pan	
	- Oil specifications	
	For fuel contamination	
	- Oil change interval	
	 For engine oil in torque converter 	
-02	– Perform checks in Step 01	1.0
	- Check:	
	Oil temperature	
	 Air compressor oil consumption 	
	 Turbocharger seal 	
	 Crankcase blowby 	

In the above example, the time required to perform the checks in Step 01 is 0.4 hour. If the problem is not located while performing the checks in Step 01, an additional 0.6 hour is allowed to perform the checks in Step 02 for a total of 1.0 hour. The total troubleshooting time appropriate is the time indicated in the column directly in line with the final step required to locate the problem. The step required to locate the problem may or may not be the last step shown in the troubleshooting SRT. Each step contains information as to which steps are included.

Repair SRTs

Repair SRTs make up the majority of this manual. These are the SRTs that cover the actual repair work. The time shown on the same line as the SRT code and title is the total time for that SRT.

Standard Repair Combined Times

Standard Repair Combined Times (SRCTs) provide for the combining of the three types of SRTs under one code so that, if appropriate, the user can identify the work performed with fewer SRT codes.



Manual Organization

SRT Coding System

Each SRT has a unique code so that SRT data can be computerized. The numbering system used is common to all the SRT manuals for all Onan engines and generator sets. The portion of the system shown in the manual contains three segments:

"Group Number"	"Procedure Number"	"Step Number"
XX	XXX	XX

Group Numbers

Group numbers (the first two digits in the SRT code) are used to identify major engine components. The following list explains the group numbers used in SRT manuals:

Procedure Numbers

The procedure number consists of three digits. The first digit provides guidance as to the category of the repair. The second and third digits, shown as XX in the following list, are sequential numbers or alpha within the category.

Group Number	Contents of Group	Specific Repair Number	Description of Category
00	Complete Engine or		
	Generator Set		
01	Cylinder Block	0XX	Troubleshooting
02	Cylinder Head		ONLY in Group 00
03	Rocker Levers	1XX	Remove and Install
04	Cam Followers/Tappets	2XX	Rebuild
05	Fuel System	3XX	Replace
06	Injectors and Fuel Lines	4XX	Clean and Visually Check or Inspect for Reuse
07	Lubricating Oil System		
80	Cooling System	5XX	Machine/Ream/Dowel/
09	Drive Units		Sleeve
10	Intake Air System		Modify/Cut/Lap
11	Exhaust System	6XX	Adjust/Calibrate
12	Air (Compressed) System		_
13	Electrical Equipment	7XX	Test
14	Engine or Generator Set Testin	g	
15	Instruments and Controls		
16	Mounting Adaptations		
17	Miscellaneous	9XX	(SRCT in Group 99) General/Miscellaneous
21	Generator Equipment		
22	Hardware		
25	Generator Components		
26	Generator Control Components	3	
27	Transfer Switches		
99	SRCT		



Step Numbers

While all SRT codes will contain a Group and Procedure number, only those procedures that are broken down into steps have step numbers. The step numbers are sequential within a SRT.

General

There is an alphabetic index in the back of the manual. Within a particular group the procedures are arranged in alphabetical order by title, thus are not in code numeric order.

There is also a numerical index in which the procedures are arranged in numeric order and not in alphabetical order.

Within a procedure, the user will note that some lines are indented. This indentation is intended to indicate that the sub-tasks are part of the task under which they are indented.

How Standard Repair Times are Developed

Cummins/Onan SRT Objectives and Philosophy

The objective of the Cummins/Onan SRT program is to provide credible and equitable labor time standards and procedures to the worldwide Cummins/Onan service network.

An SRT is credible when the procedure accurately depicts the work that **must** be performed to accomplish a quality engine or generator set repair.

An SRT is equitable when it can be performed in a period of time less than or equal to the standard by a journeyman mechanic after he/she has performed that repair at least once.

To establish credible and equitable SRTs with sufficient flexibility to account for differences in complaints, failures, progressive damage, customer desires, etc., SRTs have been structured using the following considerations:

- What must ALWAYS be done to the engine or generator set to perform the work.
- What MAY have to be done to the engine or generator set parts dependent on their condition.
- What MAY have to be removed to access the engine or generator set.
- How difficult it is for the mechanic to reach the engine or generator set even after interfering application hardware has been removed.

While the most frequent use of SRT information is the Onan Warranty System, it is Onan's intent that the SRTs be applicable to repairs conducted for any customer.

As SRTs are developed, it is assumed:

- That all the required tools, equipment, and supplies are available in sufficient quantity and in operating condition.
- That required Onan Service Manuals are available to the mechanic are being used.
- That the correct parts are available when the mechanic needs them.



How Times are Developed

SRTs are developed from time studies conducted in the field and Onan Technical Service Personnel. Technical Service Representatives create a comprehensive list of all the work elements or tasks required to perform specific repairs. Field studies are analyzed to find these same work elements or tasks and determine the time required for each. The time for work elements or tasks that are not included in the field time studies is determined by conducting free engine or generator set studies or by estimation using similar elements from existing time studies. A time is determined for each element of the procedure. The time for all elements is then totaled to establish the total productive repair time.

Productive Repair Time

Productive Repair Time is described as the actual time involved doing productive work, such as: removing, disassembling, cleaning, inspecting, machining, installing and adjusting parts or components. In addition, the following operations are considered to be productive work for inclusion in an SRT:

- Clock on and off the job or repair order, including shift changes.
- Move vehicle, engine or generator set to and from the work area.
- Move tool box to the work area.
- Obtain tools from tool box, wipe and put away after use.
- Refer to service manuals.
- Obtain, unpack and clean replacement parts as necessary.
- Package and mark parts removed as necessary for warranty or local consumer laws.
- Operate engine or generator set to check for proper operation.
- Clean work area at completion of shift or repair.
- Properly dispose of used engine fluids such as oil and coolant.
- Write summary of work performed at completion of repair or work shift.
- Help from another mechanic (time for one man to complete the task times two).

Time Allowances

After the total productive time is established, an additional allowance of 15 percent is added to cover the following:

- Personal time of 5 percent for:
 - Scheduled rest breaks
 - Personal phone calls
 - Restroom breaks
 - Shift changes
- Supplementary time of 10 percent to cover normal work interruptions:
 - Seized or hard turning fasteners
 - Extra time for extremely dirty equipment
 - Excessive waiting time for replacement parts
 - Brief assistance to other mechanics (less than 5 minutes)
 - Routine maintenance (not repair) of shop equipment
 - Obtain consumable supplies
 - Technical consultation with shop supervision



The following is an example of how the allowances are calculated to establish the SRT for a procedure where the productive time is 208.7 minute (3.48 hr):

Allowance	Allowance	Time
Туре	Percent (%)	(Minutes)
Productive Repair Time	100	208.7
Personal	5	10.4
Supplementary	<u>10</u>	20.9
TOTAL	115	240.0

Published Standard Repair Time = 4.0 hours

Work Not Included in An SRT

For almost every complete repair there will be one SRT that contains most of the work performed. This is sometimes called a base repair. For example, repairing an engine for high oil consumption often requires use of the SRT title Piston and Rings – Remove and Install. This SRT contains most of the time appropriate for the repair, so it is the base repair. There can be work required that is **not** part of this base SRT. This does not mean that the other work is non–productive, rather that other work is **NOT** required EVERY TIME the pistons and rings are removed and installed. More often than not, this other work is covered by another SRT. If the other work is **not** included in the base repair or in another SRT, the work is probably still productive work required for that particular repair.

Non-Productive Work

Analysis of past SRT time studies reveals the following general types of work that were not considered to be productive:

- Waiting on camshaft gears to heat and cool
- Waiting on another mechanic to finish using special tools or shop equipment
- Hunting for misplaced parts
- Repairing shop equipment
- Sorting through capscrews, to find the correct length, that were all thrown together into one basket during disassembly
- Repairing customer supplied components
- Salvaging parts or tools that have been damaged from improper handling or lack of correct tools
- Clearing off tables, parts carts, parts racks etc. left dirty or loaded with parts from previous repairs on other equipment
- Rework caused by installation of incorrect parts or incorrect installation of correct parts
- Fabrication or modification of special tools or equipment because the correct tools or equipment are not available
- Visiting during non-break time
- Conducting business with tool vendors
- Waiting on other mechanics to provide required help



- Waiting on parts clerk to fill orders for other mechanics
- Unnecessary inspection of new parts
- "Hot Setting" valves and injectors when not required
- Repairs to application hardware
- Rework resulting from failure to follow recommended service practices
- Performing work that is **not** part of the repair order or helping another mechanic

Service Accessibility Codes

Service repairs are affected by engine or generator set accessibility. The more difficult the accessibility, the longer it will take to complete the tasks given in the SRT procedure. Accessibility for a particular application is determined by reviewing the application and rating the degree of difficulty for performing the 20 most common repairs. Four codes (A, B, C and D) are used to classify the degree of difficulty for the service accessibility of a specific model or type of equipment. An "A" accessibility code indicates the engine or generator set is easily accessible. A "D" code indicates the application does not make the engine or generator set as easily accessible, thus the highest degree of difficulty relative to SRT standards. An "S" code is included for special or specific repairs not covered in the other four classifications. The "R" code indicates the repair is completed with the component, engine or generator set removed from the application.

"A" Accessibility Rating

- 1. Engine or generator sets mounted in equipment where 90 percent of the work can be performed while standing on the ground, shop floor, or flat work deck.
- 2. Engine or generator set can be accessed without removing any doors or panels.
- 3. Interfering application hardware can all be removed.
- 4. Clearance is sufficient for hands, wrenches, and drain and fill operations, making visual checks and room to stand and work.

"B" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 70 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine can be gained by removing access panels or doors.
- 3. On 80 percent of the operations, interfering application hardware can be removed.
- 4. On 80 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and room to stand and work.



"C" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 50 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine or generator set can be gained by removing the hood, structural members (bolted in) or sheet metal panels.
- 3. On 60 percent of the operations, interfering application hardware can be removed.
- 4. On 60 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and room to stand and work.

"D" Accessibility Rating

- 1. Engine or generator set mounted in equipment where 25 percent of the work can be performed while standing on the ground, shop floor or flat work deck.
- 2. Access to the engine or generator set is limited due to interference from permanently mounted structural members, sheet metal or crossmembers.
- On 40 percent of the operations, clearance is sufficient for hands, wrenches, service tools, drain and fill operations, making visual checks and limited room to stand and work.

Standard Repair Combined Times (SRCTs)

SRCTs are the combination of some of the SRTs in the manual within a distinctive code. These SRCTs are based on field input of SRTs that are most frequently used in combination to describe the most common field repairs on this engine.

The use of SRCTs can reduce the amount of time required to determine the labor standard for a specific complete engine or generator set repair. The use of SRCTs will also reduce the number of codes required when completing a warranty claim or customer invoice.

SRCTs are intended to supplement, NOT replace, SRTs. One SRCT code can be used instead of several SRT codes.

It is intended that other appropriate SRTs can be used to supplement an SRCT as long as the work does not overlap. If there is overlapping work, do **not** use an SRCT.



How To Use This Manual

1. Determine the actual work performed:

Obtain this information from the work description on the repair order.

2. Determine the Accessibility Code:

- Determine the application from the repair order.
- Look in the "Accessibility Code Listing" on page to determine the accessibility code for the application involved in the repair. If the application is not shown, assume the accessibility code is "B".
- Write down the code.

3. Determine applicable SRCT:

- Find the Contents Page for Group 99 Standard Repair Combined Times.
- Compare the titles to the work performed to determine if a SRCT will apply.
- If there is an SRCT that seems to apply, find that SRCT and compare the SRT within the SRCT to the work performed. If you are not sure of the work included in the SRT, read that SRT and compare the procedure listing with the work performed.
- If an SRCT applies to all or part of the work performed, find the column that contains the same accessibility code determined in Step 2 above.
- Move down the column to the line containing the SRCT code and title and pick out the appropriate time.
- If all the work in the SRCT is performed and additional steps were taken, use the SRCT and continue to Step 4 to cover the additional work.
- If there is NOT an appropriate SRCT, move to Step 4.

4. Determine the appropriate repair SRT:

- Use the information from the repair order to identify the parts involved.
- Use the contents page at the front of the manual or the alphabetical index in the back of the manual to determine the appropriate SRT group for the parts and/or work involved.
- Find the contents page for that group.
- Read the contents page for procedure titles that seem to correspond to the work performed.
- Find the SRT within the group.
- Read the SRT procedure listing to determine the work included.



- If the work performed and the work included in the SRT are the same, all or in part, determine and record the time.
- Repeat the steps in this paragraph until you have determined a SRT for all the work performed.

5. Determine the appropriate troubleshooting SRT:

- Read the repair order to determine what troubleshooting work was performed.
- Find the contents page for Group 00.
- Read the contents page for procedure to determine the work included in each step.
- If the work performed and the work included in the troubleshooting SRT are the same, all or in part, determine and record the time of the SRT step. Remember that troubleshooting SRTs are cumulative.

6. Determine the appropriate miscellaneous SRT:

- Read the repair order to determine if any application hardware was removed and installed in order to access the engine or generator set.
- Find the contents page for Group 17.
- Read the contents page for procedure titles that seem to correspond to the work performed.
- Find the SRT within the group.
- Read the SRT procedure to determine the work included in the SRT.
- If the work performed and the work included in the SRT are the same, all or in part, determine and record the time.
- If the work required to application hardware is not given in the SRT manual, determine the time for ONLY this work from the repair order. Record the time for possible use as "99–999" or "Non-SRT Time".

7. Determine the appropriate administrative SRT:

- Both of the administrative SRTs are shown at the beginning of Group 00.
- Determine the appropriate SRT.
- Record the time.



8. Determine the total appropriate SRT time:

- Check to be sure that there is no duplication of tasks within the SRT procedures selected. If there is work duplicated by some of those selected, use other information contained in the manual to reduce the time of one of the SRTs accordingly. If the information is not available, make an estimate.
- Total all the times obtained during performance of Steps 2 through 7.

Standard Repair Times Review Procedure

Onan Corporation makes every effort to be sure the SRTs published in this manual are credible and equitable. It will be necessary to review the published times when one or more of the following changes occur:

- Design changes to special service tools or equipment required to perform the repair
- Changes to the repair procedure

A formal SRT review procedure is available for any Cummins/Onan Authorized Repair Location that believes the SRTs shown in this manual are incorrect.

To be sure prompt attention and an accurate appraisal is given to your request, the following quidelines must be met:

- 1. Be sure the technician has followed all the procedures and used all the service tools referred to in the appropriate service manuals.
- 2. Be sure a journeyman technician performed the repair, one who has completed the repair a sufficient number of times to become familiar with the procedure.
- 3. Be sure all the SRTs, including supplemental SRTs, appropriate for the repair are being used.
- 4. Include as much detail as possible about the specific repair.

NOTE: It is **NOT** the intent of this procedure to provide a forum for appealing or disputing the amount of time or the SRT judged appropriate on a particular warranty claim. Communication of this sort **must** follow the processes shown in the Onan Warranty Administration Manual.

- 5. Provide photographs of the installation.
- 6. Provide copies of all repair orders applicable to the SRTs involved, the technicians time cards, and any other information related to the repair that will aid in the review process.
- 7. Be sure to provide the correct name of the repairing location, a phone number, and point of contact.



Company Action

Upon receipt of the request for an SRT review, the following action will be taken:

- 1. The person signing the request will be contacted to acknowledge the receipt of the request.
- 2. All the information provided will be analyzed and compared with the history files of the specific operation.
- 3. All information will be analyzed to determine if an error has been made in the procedure, the operations description, or the published repair time.
- 4. If it is determined the published repair time is incorrect, additional studies/analysis will be performed to establish the correct time. The requester will be notified of the results, and the results will be published in the next SRT update.
- 5. If it is determined that the time and procedure is correct, recommendations and assistance will be offered as needed.





Group 00 – Complete Engine or Generator Set

Contents

Open/Close Repair Order (Shop)
Dpen/Close Repair Order (Road)
ıbleshoot (Genset)
Ingine Will Not Crank
Genset Starts But Stops After Switch Releases
ligh/Low AC Output
lo AC Output Voltage
Instable Voltage with Stable Engine
Inbalanced Output Voltage
ingine Oil Leak
Coolant Loss
Genset Cranks But Will Not Start
Genset Unstable (Hunts)
excessive Smoke Under Load (Overload Condition)
xcess White Smoke at Start-Up (Warm)
excess White Smoke at Start-Up (Cold)
ıbleshoot (Fault Codes)
ault Code 1 (High Engine Temperature)
ault Code 2 (Low Oil Pressure)
ault Code 4 (Overcrank)
ault Code 7 (Loss of Raw Water Flow)
ault Code 12 (Overvoltage)
ault Code 13 (Undervoltage)
ault Code 13 (Undervoltage)
ault Code 14 (Overfrequency)
ault Code 14 (Overfrequency)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow) ault Code 41 (Grounded Rotor)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow) ault Code 41 (Grounded Rotor) ault Code 42 (Control Card ROM)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow) ault Code 41 (Grounded Rotor) ault Code 42 (Control Card ROM) ault Code 43 (Control Card RAM)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow) ault Code 41 (Grounded Rotor) ault Code 42 (Control Card ROM) ault Code 43 (Control Card RAM) ault Code 48 (Control Card Field Voltage Sense)
ault Code 14 (Overfrequency) ault Code 15 (Underfrequency) ault Code 17 (Overprime) ault Code 22 (Actuator Overload) ault Code 23 (Faulty Oil Pressure Sender) ault Code 24 (Faulty Temperature Sender) ault Code 27 (Loss of Voltage Sense) ault Code 29 (High Battery Voltage) ault Code 35 (Control Card EE Checksum) ault Code 36 (Engine Stopped) ault Code 37 (Invalid Set Configuration) ault Code 38 (Field Overflow) ault Code 41 (Grounded Rotor) ault Code 42 (Control Card ROM) ault Code 43 (Control Card RAM)



	Page
Genset (Below Deck)	18
Remove And Install	18
Engine	
Genset Engine Assembly	



Procedure Number and Description R A B C 00–901 Administrative Time – Open/Close Repair Order (Shop) Includes: - Clock on and off the job - Move equipment to and from work area - Clean work area	cessibility Codes Special C D S
00–901 Administrative Time – Open/Close Repair Order (Shop) Includes: - Clock on and off the job - Move equipment to and from work area	•
(Shop) Includes: - Clock on and off the job - Move equipment to and from work area	
- Clock on and off the job - Move equipment to and from work area	
Move equipment to and from work area	
Clean work area	
– Record the following:	
Genset model number	
Genset serial number	
Customer name and address	
Genset date in service	
 Hours of operation 	
- Write repair procedures	
00–902 Administrative Time – Open/Close Repair Order 0.7 (Road)	
Includes:	
- Clock on and off the job	
Move equipment to and from work area	
- Clean work area	
– Record the following:	
Genset model number	
Genset serial number	
Customer name and address	
Genset date in service	
- Hours of operation	
- Write repair procedures	
00-0AA Troubleshoot - Engine Will Not Crank	
Includes:	
_01 _ Check: 0.3	
- Battery condition	
- Battery voltage	
- Battery connections	
- Evaluate fault codes	



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0AA	Troubleshoot - Engine Will Not Crank	-	-	-	-	-	-
-02	 Perform checks in step 01 	-	-	0.7	-	-	-
	- Check:						
	 Manual engine rotation 						
	 Wiring connections to and from control, relay, switch, and starter 						
	 K4 relay operation 						
	Start/Stop switch						
	Starter						
00-0AB	Troubleshoot – Genset Starts But Stops After Switch Releases	-	-	1.0	-	-	-
	Includes:						
	- Check:						
	 Control plugs fully seated 						
	 Field sense, quad leads fully seated in con- nector to control 						
	AC output						
	 Field voltage 						
	 Broken or loose wires 						
	 Proper field resistance reading, open to ground 						
	 Proper quadrature resistance reading open to ground and main windings 						
00-0AD	Troubleshoot – High/Low AC Output	-	-	0.3	-	-	-
	Includes:						
	- Check:						
	 Control plugs fully seated 						
	 Sense leads fully seated in connector to control 						
	 Load balance 						
	 Broken or loose wires 						
	 Output lead configuration 						
	 Evaluate fault codes 						



Sta	ndard Repair Times	Removed From Chassis	,	Service	In-Ch Acces		Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0AG	Troubleshoot - No AC Output Voltage	-	-	0.3	-	-	-
	Includes:						
	- Check:						
	 Load breaker closed 						
	 Broken or loose wires 						
	 Control plugs fully seated 						
	 Evaluate fault codes 						
00-0AH	Troubleshoot – Unstable Voltage with Stable Engine	-	-	0.3	-	-	-
	Includes:						
	- Check:						
	 Evaluate fault codes 						
	 Proper output lead connection 						
	 Genset output voltage 						
	 Voltage at line side of genset breaker 						
	 Voltage at load side of genset breaker 						
	 Sensor leads fully seated in connector to control 						
	 Control plugs fully seated 						
00-0AZ	Troubleshoot – Unbalanced Output Voltage	-	-	0.5	-	-	-
	Includes:						
	- Check:						
	 Evaluate fault codes 						
	 Proper output lead connection 						
	 Genset output voltage 						
	 Voltage at line side of genset breaker 						
	 Voltage at load side of genset breaker 						
	 Load at genset breaker 						
	 Output lead configuration 						
	 Control plugs fully seated 						
	 Sense leads fully seated in connector to control 						
							<u> </u>



Sta	ndard Repair Times	Removed From Chassis	,	Service		nassis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0CM	Troubleshoot - Engine Oil Leak	-	-	-	-	-	-
	Includes:						
-01	 Clean contaminated area 	-	-	0.4	-	-	-
	- Check:						
	Oil level						
	 Loose hose or drain fittings 						
	Oil filter seal						
-02	Perform checks in step 01Check:	-	-	1.0	-	-	-
	Leaks while running with dye in oil						
	Evaluate fault codes						
	- Evaluate fault codes						
00-010	Troubleshoot - Coolant Loss	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	 Evaluate fault codes 						
	 Coolant level 						
	 Cracked or leaking hoses 						
	 Loose hose clamps 						
	Coolant in oil						
-02	 Perform checks in step 01 	-	-	1.0	_	-	-
	- Check						
	 Pressure test cooling system (cold) 						
	 Pressure test cooling system (hot) 						
00-022	Troubleshoot – Genset Cranks But Will Not Start	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.7	_	-	-
	 Evaluate fault codes 						
	Fuel supply						
	 Fuel from fuel pump 						
	Glowplugs						
	 Governor actuator operation 						
1					1		



Sta	ndard Repair Times	Removed From Chassis	:	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-022	Troubleshoot – Genset Cranks But Will Not Start	-	-	-	-	-	-
-02	 Perform checks in step 01 	-	-	1.5	-	-	-
	- Check:						
	 Cylinder compression 						
00-041	Troubleshoot – Genset Unstable (Hunts)	-	-	0.7	-	-	-
	Includes:						
	- Check:						
	 Evaluate fault codes 						
	Fuel supply						
	 Loose wire connections 						
	 Governor actuator operation 						
00–046	Troubleshoot – Excessive Smoke Under Load (Overload Condition)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	 Evaluate fault codes 						
	Fuel supply						
	Fuel filters						
-02	 Perform checks in step 01 	-	-	0.7	-	-	-
	- Check:						
	 Intake restriction 						
-03	 Perform checks in step 02 	-	-	1.2	-	-	-
	- Check:						
	Fuel flow						
	 Governor actuator operation 						
00–047	Troubleshoot – Excess White Smoke at Start-Up (Warm)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.3	-	-	-
	 Low engine temperature 						
	Low raw water flow (steam)						



Sta	ndard Repair Times	Removed From Chassis		Service		assis sibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00–047	Troubleshoot – Excess White Smoke at Start-Up (Warm)	-	-	-	-	-	-
-02	 Perform checks in step 01 	-	-	1.5	-	-	-
	- Check:						
	 Engine compression 						
00-048	Troubleshoot – Excess White Smoke at Start-Up (Cold)	-	-	0.5	-	-	-
	Includes:						
	- Check						
	 K3 relay operation 						
	Glowplugs						
00-0CV	Troubleshoot – Fault Code 1 (High Engine Temperature)	-	-	-	-	-	-
	Includes:						
	For MDKAV, MDKAW, MDKAZ, and MDKBG Gensets						
-01	- Check:	-	-	1.0	-	-	-
	 Coolant temperature 						
	 Coolant level 						
	 Temperature sender resistance 						
	 Control plugs fully seated 						
	 Grounded or shorted sender or gauge lead 						
	 Sender to control 						
	 Control to plug P13 						
	 Plug P13 to gauges (if equipped) 						
	 Good ground connection to gauge remote or local (if equipped) 						
	 Good B+ connection to gauge remote or local (if equipped) 						
	For MDKBK, MDKBL, MDKBM, and MDKBN Gensets						
-01	- Check:	-	-	1.0	-	-	-
	 Coolant temperature 						
	 Coolant level 						
	 Temperature sender resistance 						



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							Special		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
00-0CV	Troubleshoot – Fault Code 1 (High Engine Temperature)	-	-	-	-	-	-		
	 Control plugs fully seated 								
	 Grounded or shorted sender or gauge lead 								
	 Sender to control 								
-02	 Perform checks in step 01 	-	-	1.5	-	-	-		
	- Check:								
	 Raw water flow 								
	 Raw water impeller 								
	 Heat exchange blockage 								
	 Pressure cap 								
00-0CF	Troubleshoot – Fault Code 2 (Low Oil Pressure)	-	-	-	-	-	_		
	Includes:								
	For MDKAV, MDKAW, MDKAZ, and MDKBG Gensets								
-01	- Check:	-	-	1.0	-	-	-		
	Oil level								
	 Pressure sender resistance 								
	 Control plugs fully seated 								
	 Broken or loose sender lead 								
	 Sender to control 								
	Control to plug P13								
	 Plug P13 to gauges (if equipped) 								
	 Good ground connection to gauge remote or local (if equipped) 								
	 Good B+ connection to gauge remote or local (if equipped) 								
	For MDKBK, MDKBL, MDKBM, and MDKBN Gensets								
-01	- Check:	_	_	1.0	_	_	_		
	- Oil level								
	Pressure sender resistance								
	Control plugs fully seated								
	 Broken or loose sender lead 								



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
00-0CF	Troubleshoot – Fault Code 2 (Low Oil Pressure)	-	-	-	-	-	-		
	 Sender to control 								
-02	 Perform checks in step 01 	-	-	1.5	-	-	-		
	- Check								
	 Oil pressure (mechanical) 								
00-0CG	Troubleshoot – Fault Code 4 (Overcrank)	-	-	-	-	-	-		
	Includes:								
-01	- Check:	-	-	0.5	-	-	-		
	 Battery voltage 								
	Fuel supply								
	 Governor actuator operation 								
	 Control plugs fully seated 								
	 Field resistance 								
	 Quadrature resistance 								
-02	 Perform checks in step 01 	-	-	1.5	-	-	-		
	- Check								
	 Cylinder compression 								
00-0CW	Troubleshoot – Fault Code 7 (Loss of Raw Water Flow)	-	-	-	-	-	-		
	Includes:								
-01	- Check:	-	-	0.4	-	-	-		
	 Raw water supply 								
	 Raw water flow 								
	 Grounded or shorted S6 switch leads 								
-02	 Perform checks in step 01 	-	-	1.0	-	-	-		
	Check								
	 Raw water impeller 								
	 Blocked heat exchanger 								
1]		1		1			



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0BD	Troubleshoot – Fault Code 12 (Overvoltage)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	 Output voltage 						
	- Loads						
	Fuel supply						
	 Sense leads fully seated in connector to control 						
	 Control plugs fully seated 						
-02	 Perform checks in step 01 	-	-	1.0	-	-	-
	Check						
	 Grounded or shorted field windings 						
	 Grounded or shorted stator windings 						
00-0BE	Troubleshoot – Fault Code 13 (Undervoltage)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	Output voltage						
	- Loads						
	Fuel supply						
	 Sense leads fully seated in connector to control 						
	 Control plugs fully seated 						
-02	 Perform checks in step 01 	-	-	1.0	-	-	-
	- Check						
	 Grounded or shorted field windings 						
	 Grounded or shorted stator windings 						
-03	 Perform checks in step 02 	-	-	2.0	-	-	-
	- Check						
	 Rotating diode assembly 						
	Main rotor						
	 Exciter rotor 						
						<u> </u>	



Standard Repair Times		Removed From Chassis	;	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0BF	Troubleshoot – Fault Code 14 (Overfrequency)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	Engine speed (frequency)						
	- Loads						
	Fuel supply						
	 Quad leads fully seated in connector to control 						
	 Control plugs fully seated 						
-02	 Perform checks in step 01 	-	-	1.0	-	-	-
	- Check						
	 Governor actuator operation 						
00-0BG	Troubleshoot – Fault Code 15 (Underfrequency)	-	-	-	-	-	-
	Includes:						
-01	- Check:	-	-	0.5	-	-	-
	Engine speed (frequency)						
	- Loads						
	Fuel supply						
	 Quad leads fully seated in connector to control 						
	 Control plugs fully seated 						
-02	 Perform checks in step 01 	-	-	1.0	-	-	-
	- Check						
	 Governor actuator operation 						
00-0BH	Troubleshoot – Fault Code 17 (Overprime)	-	-	0.4	-	-	-
	Includes:						
	Check						
	 Battery voltage 						
	Fuel supply						
	 Start/stop switch (local and remote) 						
	Open / shorted wiring						



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							Special		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
00-0BL	Troubleshoot – Fault Code 22 (Actuator Overload)	-	-	-	-	-	-		
	Includes:								
-01	- Check:	-	-	0.3	-	-	-		
	- Load								
	Fuel supply								
-02	 Perform checks in step 01 	-	-	0.5	-	-	-		
	- Check								
	 Intake restriction 								
-03	 Perform checks in step 02 	-	-	0.7	-	-	-		
	- Check								
	 Governor actuator operation 								
00-0BM	Troubleshoot – Fault Code 23 (Faulty Oil Pressure Sender)	-	-	-	-	-	-		
	Includes:								
	For MDKAV, MDKAW, MDKAZ, and MDKBG Gensets								
-01	- Check:	-	-	0.7	-	-	-		
	Oil level								
	 Pressure sender resistance 								
	 Control plugs fully seated 								
	 Broken or loose sender lead 								
	 Sender to control 								
	Control to plug P13								
	 Plug P13 to gauges (if equipped) 								
	 Good ground connection to gauge remote or local (if equipped) 								
	 Good B+ connection to gauge remote or local (if equipped) 								
	For MDKBK, MDKBL, MDKBM, and MDKBN Gensets								
-01	- Check:	-	-	0.7	-	-	-		
	Oil level								
	 Pressure sender resistance 								



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis sibility	Codes
	Procedure Number and Description	R	Α	В	С	D	<u>Special</u> S
	(continued from previous page)	1					
00-0BM	Troubleshoot – Fault Code 23 (Faulty Oil Pressure Sender)	-	-	-	-	-	-
	 Control plugs fully seated 						
	 Broken or loose sender lead 						
	 Sender to control 						
-02	 Perform checks in step 01 	-	-	1.0	-	-	-
	- Check						
	Oil pressure (mechanical)						
00-0BN	Troubleshoot – Fault Code 24 (Faulty Temperature Sender)	-	-	-	-	-	-
	Includes:						
	For MDKAV, MDKAW, MDKAZ, and MDKBG Gensets						
-01	- Check:	-	-	0.7	-	-	-
	 Coolant temperature 						
	 Coolant level 						
	 Temperature sender resistance 						
	 Control plugs fully seated 						
	 Grounded or shorted or grounded sender or gauge lead 						
	 Sender to control 						
	 Control to plug P13 						
	 Plug P13 to gauges (if equipped) 						
	 Good ground connection to gauge remote or local (if equipped) 						
	 Good B+ connection to gauge remote or local (if equipped) 						
	For MDKBK, MDKBL, MDKBM, and MDKBN Gensets						
-01	- Check:	-	-	0.7	-	-	-
	 Coolant temperature 						
	 Coolant level 						
	 Temperature sender resistance 						
	 Control plugs fully seated 						



Sta	ndard Repair Times	Removed From		Sorvice		assis	Codos
		Chassis	•	Jervice	Acces	Sibility	Codes
						_	<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
00-0BN	Troubleshoot – Fault Code 24 (Faulty Temperature Sender)	-	-	-	-	-	-
	 Grounded or shorted or grounded sender or gauge lead 						
	 Sender to control 						
-02	 Perform checks in step 01 	-	-	1.3	-	-	-
	Check						
	 Raw water flow 						
	 Raw water impeller 						
	 Heat exchanger blockage 						
	Pressure cap						
00-0BU	Troubleshoot – Fault Code 27 (Loss of Voltage Sense)	-	-	1.0	-	-	-
	Includes:						
	- Check						
	 Broken or loose voltage sense leads 						
	 Sense leads fully seated in connector to control 						
	 Control plugs fully seated 						
	AC output						
	 Field resistance 						
	 Main stator resistance 						
00-0BR	Troubleshoot – Fault Code 29 (High Battery Voltage)	-	-	0.3	-	-	-
	Includes:						
	- Check						
	 Battery voltage 						
	 Battery connections 						
	 Battery charge rate 						
00-0CA	Troubleshoot – Fault Code 35 (Control Card EE Checksum)	-	-	0.3	-	-	-
	Includes:						
	- Check						
	Verify fault						



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0CA	Troubleshoot – Fault Code 35 (Control Card EE Checksum)	-	-	0.3	-	-	-	
00-0BW	Troubleshoot – Fault Code 36 (Engine Stopped)	-	-	_	-	-	-	
	Includes:							
-01	- Check:	-	-	0.5	-	-	-	
	Fuel supply							
	 Mechanical engine damage 							
	Output voltage							
	- Loads							
	 Quad leads fully seated in connector to control 							
	 Control plugs fully seated 							
-02	 Perform checks in step 01 	_	-	1.0	-	-	-	
	- Check							
	 Governor actuator operation 							
	 Grounded or shorted field windings 							
	 Grounded or shorted quad windings 							
-03	 Perform checks in step 02 	-	-	2.0	-	-	-	
	- Check							
	 Rotating diode assembly 							
	Main rotor							
	Exciter rotor							
00-0CH	Troubleshoot – Fault Code 37 (Invalid Set Configuration)	-	-	0.5	-	-	-	
	Includes:							
	- Check							
	 Broken or loose wiring connections 							
	 Configuration plug P8 is fully seated 							
	 Proper control part number 							
00-0BX	Troubleshoot – Fault Code 38 (Field Overflow)	-	-	-	-	-	-	
	Includes:							
-01	- Check:	-	-	0.5	-	-	-	
	Output voltage							



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0BX	Troubleshoot - Fault Code 38 (Field Overflow)	-	-	-	-	-	-	
	Frequency							
	- Loads							
-02	 Perform checks in step 01 	_	-	1.0	-	_	_	
	– Check							
	 Field resistance 							
	 Main stator resistance 							
-03	Perform checks in step 02		_	2.0	_			
_00	- Check			2.0			_	
	Rotating diode assembly							
	Main rotor resistance							
	- Exciter rotor							
	27010110101							
00-0CI	Troubleshoot – Fault Code 41 (Grounded Rotor)	-	-	0.3	-	-	-	
	Includes:							
	Check							
	Verify fault							
00-0CB	Troubleshoot – Fault Code 42 (Control Card ROM)	-	-	0.3	-	-	-	
	Includes:							
	- Check							
	Verify fault							
00-0CC	Troubleshoot – Fault Code 43 (Control Card RAM)	-	-	0.3	-	-	-	
	Includes:							
	- Check							
	Verify fault							
00-0CD	Troubleshoot – Fault Code 48 (Control Card Field Voltage Sense)	-	-	0.3	-	-	-	
	Includes:							
	- Check							
	Verify fault							



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-0AN	Troubleshoot – Fault Code 58 (High Exhaust Temp)	-	-	0.5	-	-	-	
	Includes:							
	Check							
	 Broken or loose switch leads 							
	 Exhaust temperature switch S5 							
	 Raw water flow 							
00-0CX	Troubleshoot – Fault Code 61 (Emergency Shutdown)	-	-	0.3	-	-	-	
	Includes:							
	- Check							
	 Customer input connections 							
	 K5 relay operation (if equipped) 							
00-1AB	Genset (Above Deck) – Remove And Install	-	-	4.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Output leads 							
	Fuel lines							
	 Exhaust system 							
	 Raw water supply 							
	 Remove and install 							
	Genset							
	 Test run unit 							
00-1AC	Genset (Below Deck) – Remove And Install	-	-	13.0	_	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	Output leads							
	– Fuel lines							
	Exhaust system							
	Raw water supply							



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
		211100.0				- 7	Special		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)			_		_			
00-1AC	Genset (Below Deck) – Remove And Install	-	-	13.0	_	_	-		
	Remove and install								
	- Genset								
	 Test run unit 								
00–201	Engine – Rebuild	-	-	16.0	-	-	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	 Coolant hose 								
	 Exhaust hose 								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	 Generator control 								
	 Generator end 								
	Flywheel								
	Flywheel housing								
	 Intake manifold 								
	 Exhaust Manifold 								
	 Coolant pump belt drive 								
	 Coolant pumps 								
	 Coolant hoses 								
	 Governor actuator 								
	 Fuel injection supply and return lines 								
	Fuel injection pump								
	 Valve cover rocker assembly and pushrods 								
	 Cylinder head and gasket 								
	– Lifters								
	 Crankshaft pulley 								
	 Gearcase cover and gasket 								
	 Oil pan and gasket 								
	 Piston and connecting rods 								



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
00-201	Engine – Rebuild	-	-	16.0	-	-	-	
	 Rod bearings 							
	 Oil pump drive gear 							
	 Oil pump and gasket 							
	 Rear main seal carrier 							
	Idler gear							
	Camshaft							
	Fuel camshaft							
	Crankshaft							
	 Main bearing carrier and bearings 							
	Oil seals							
	 Clean and visually inspect 							
	Crankshaft							
	Camshafts							
	 Cylinder block 							
	 Hone cylinder (as needed) 							
	 Torque cylinder head 							
	 Adjust valve lash 							
	 Test run unit 							
00-3AB	Genset Engine Assembly – Replace	-	-	8.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hose 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Starter							
	 Generator control assembly 							
	 Generator assembly 							



Standard Repair Times	Removed From Chassis Service Accessibility Codes			Codes		
						<u>Special</u>
Procedure Number and Description	R	Α	В	С	D	S
(continued from previous page)						
00-3AB Genset Engine Assembly - Replace	-	-	8.0	-	-	-
 Transfer parts to new engine 						
Flywheel						
 Flywheel housing 						
 Intake manifold 						
 Exhaust Manifold 						
Starter						
 Switches and senders 						
 Engine mounts 						
 Raw water pump 						
 Fuel filter assembly and lines 						
Fuel pump						
 Test run unit 						





Group 01 – Cylinder Block

	Page
Camshaft, Valve	24 24
Camshaft, Fuel	24 24
Connecting Rod	25 25
Connecting Rod Bearings	26 26
Crankshaft Remove And Install	27 27
Gear, Crankshaft	28 28
Gear Case Cover	28 28
Piston	29 29
Crankshaft Seal, Front	30
Crankshaft Seal, Rear	30



Sta	ndard Repair Times	Removed From				assis	
	•	Chassis	,	Service	Acces	ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
01-3AE	Camshaft, Valve – Replace	_	_	12.0	_	_	_
OI-JAL	Includes:			12.0			
	Disconnect and connect						
	Battery cables						
	Engine wiring harness (as needed)						
	Exhaust hose						
	- Coolant hose						
	Drain and refill engine fluids						
	Remove and install						
	Soundshield (as needed)						
	Coolant pump drive belt						
	Coolant pumps						
	Coolant hoses						
	Governor actuator						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	– Lifters						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	Camshaft stopper						
	 Camshaft and gear 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	Test run unit						
01-1AC	Camshaft, Fuel - Replace	-	-	12.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines (as needed)						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						



Sta	ndard Repair Times	Removed From Chassis	,	Service		assis sibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01-1AC	Camshaft, Fuel – Replace	-	-	12.0	-	-	-
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Governor actuator 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	 Injection pump 						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	Idler gear						
	 Camshaft, fuel stopper 						
	 Camshaft assembly 						
	 Test run unit 						
01–1AA	Connecting Rod – Remove And Install	-	-	10.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines (as needed)						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator assembly 						
	 Fuel injection supply and return lines 						
	 Valve cover and rocker assembly 						
	 Cylinder head and gasket 						
	 Oil pan and gasket 						
	 Pistons and connecting rods 						
	Piston rings						



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
01–1AA	Connecting Rod – Remove And Install	-	-	10.0	-	-	-	
	 Rod bearings 							
	 Clean and visually inspect crankshaft 							
	 Hone cylinder (as needed) 							
	 Torque cylinder head 							
	 Adjust valve lash 							
	 Test run unit 							
01-3AF	Connecting Rod Bearings - Replace	-	-	10.0	-	-	-	
	Includes:							
	 Disconnect and Connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust hose 							
	Coolant hoses							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Generator assembly 							
	 Fuel injection supply and return lines 							
	 Valve cover and rocker assembly 							
	 Cylinder head and gasket 							
	 Oil pan and gasket 							
	 Pistons and connecting rods 							
	 Rod bearings 							
	 Clean and visually inspect crankshaft 							
	 Hone cylinder (as needed) 							
	 Torque cylinder head 							
	 Adjust valve lash 							
	Test run unit							



Sta	indard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
01–112	Crankshaft – Remove And Install	-	-	14.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Generator assembly 							
	Flywheel							
	 Flywheel housing 							
	 Coolant pump drive belt 							
	 Coolant pumps 							
	 Coolant hoses 							
	 Governor actuator 							
	 Fuel injection supply and return lines 							
	 Valve cover rocker assembly and pushrods 							
	 Cylinder head and gasket 							
	Lifters							
	 Crankshaft pulley 							
	 Gearcase cover and gasket 							
	 Oil pan and gasket 							
	 Pistons and connecting rods 							
	Rod bearings							
	 Oil pump drive gear 							
	 Oil pump and gasket 							
	 Rear main seal carrier 							
	Crankshaft							
	 Main bearing carrier and bearings 							
	Oil seals							
	 Clean and visually inspect crankshaft 							
	 Hone cylinder (as needed) 							



Sta	ndard Repair Times	Removed From Chassis		Service		assis	Codes
		Onassis			1 10000		Special
	Procedure Number and Description	R	Α	В	С	D	S S
	(continued from previous page)	11			0		0
01–112	Crankshaft – Remove And Install	_	_	14.0	_	_	_
01-112	Torque cylinder head			14.0			
	Adjust valve lash						
	- Test run unit						
01–114	Gear, Crankshaft – Remove And Install	-	-	4.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	Coolant hoses						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Governor actuator 						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	Idler gear						
	 Crankshaft gear 						
	 Test run unit 						
01–121	Gear Case Cover - Remove And Install	-	-	4.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						



Sta	ndard Repair Times	Removed From Chassis		Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01–121	Gear Case Cover – Remove And Install	-	-	4.0	-	-	-
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Governor actuator 						
	 Crankshaft pulley 						
	 Gearcase cover and gasket 						
	 Test run unit 						
01–140	Piston – Remove And Install	-	-	10.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator assembly 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Governor actuator 						
	 Fuel injection supply and return lines 						
	 Valve cover and rocker assembly 						
	 Cylinder head and gasket 						
	– Lifters						
	 Oil pan and gasket 						
	 Pistons and connecting rods 						
	Rod bearings						
	 Clean and visually inspect crankshaft 						



Sta	ndard Repair Times	Removed From Chassis		Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01–140	Piston – Remove And Install	-	-	10.0	-	-	-
	 Hone cylinder (as needed) 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	 Test run unit 						
01–304	Crankshaft Seal, Front - Replace	-	-	3.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Coolant pump drive belt 						
	 Crankshaft pulley 						
	- Oil seal						
	 Crankshaft collet and o-ring 						
	 Test run unit 						
01–308	Crankshaft Seal, Rear - Replace	-	-	6.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	Coolant hoses						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator assembly 						



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes				Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
01–308	Crankshaft Seal, Rear - Replace	-	-	6.0	-	-	-
	Flywheel						
	 Bearing case cover 						
	- Oil seal						
	 Visually inspect for oil leaks 						
	 Test run unit 						





Group 02 – Cylinder Head

	Page
Cylinder Head Gasket	. 34
Replace	. 34
Valve Guides	. 34
Replace	. 34
Valves	. 36
Replace	. 36



Standard Repair Times		Removed From Chassis		Service	assis sibility	ssis bility Codes		
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
02-3AA	Cylinder Head Gasket – Replace	-	-	6.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Exhaust manifold 							
	 Intake resonator 							
	 Intake manifold 							
	 Coolant pump drive belt 							
	Coolant pumps							
	Coolant hoses							
	 Fuel injection supply and return lines 							
	 Valve cover rocker assembly and pushrods 							
	 Cylinder head and gasket 							
	Clean carbon off							
	Cylinder head							
	Tops of pistons							
	Around valve ports							
	Torque cylinder head							
	Adjust valve lash							
	Test run unit							
02–302	Valve Guides - Replace	-	-	8.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	 Fuel lines 							



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
02-302	Valve Guides – Replace	-	-	8.0	-	-	-	
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Exhaust manifold 							
	 Intake resonator 							
	 Intake manifold 							
	 Coolant pump drive belt 							
	 Coolant pumps 							
	 Coolant hoses 							
	 Fuel injection supply and return lines 							
	 Valve cover rocker assembly and pushrods 							
	 Cylinder head and gasket 							
	 Remove and install from head 							
	- Caps							
	 Spring collet, retainer, and spring 							
	- Stem seal							
	- Valve							
	 Valve guides 							
	 Clean carbon off 							
	 Cylinder head 							
	 Tops of pistons 							
	 Around valve ports 							
	 Lap valves of valve seats 							
	- Torque cylinder head							
	Adjust valve lash							
	– Test run unit							



Standard Repair Times		Removed From Chassis	;	Service		assis sibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
02-3AB	Valves – Replace	-	-	6.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Exhaust manifold 						
	 Intake resonator 						
	 Intake manifold 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	 Remove and install from head 						
	- Caps						
	 Spring collet, retainer, and spring 						
	Stem seal						
	Valve						
	Clean carbon off						
	Cylinder head						
	Tops of pistons						
	Around valve ports						
	 Lap valves of valve seats 						
	Torque cylinder head						
	Adjust valve lash						
	- Test run unit						



Group 03 – Rocker Levers

	Page
Valves	. 38
Adjust	. 38
Breather	
Service	. 38



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
03-603	Valves – Adjust	_	_	1.7	_	_	_	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust hose 							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Glowplugs							
	Valve cover							
	 Adjust valve lash 							
	 Test run unit 							
03-801	Breather - Service	-	-	0.7	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	Coolant hoses							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Breather cover 							
	 Breather gasket 							
	 Breather element 							
	 Test run unit 							



Group 04 – Cam Followers/Tappets

	raye
Valve Tappets	40
Remove And Install	40



Sta	Standard Repair Times		Ç	Service		assis ssibility	Codes
							Special
	Procedure Number and Description	R	Α	В	С	D	S
04–118	Valve Tappets – Remove And Install	-	-	6.0	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	Engine wiring harness (as needed)						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Exhaust manifold 						
	 Intake resonator 						
	 Intake manifold 						
	 Coolant pump drive belt 						
	 Coolant pumps 						
	 Coolant hoses 						
	 Fuel injection supply and return lines 						
	 Valve cover rocker assembly and pushrods 						
	 Cylinder head and gasket 						
	Tappets						
	Clean carbon off						
	 Cylinder head 						
	Tops of pistons						
	 Around valve ports 						
	 Torque cylinder head 						
	 Adjust valve lash 						
	 Test run unit 						



Group 05 – Fuel System

	Page
Governor Actuator	42
Replace	42
Fuel Pump, Electrical	42
Replace	42
Pump, Injection	43
Replace	43



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes				Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
05-1AB	Governor Actuator – Replace			0.5	_		_
03-145	Includes:			0.0			
	Disconnect and connect						
	Battery cables						
	Engine wiring harness (as needed)						
	- Fuel lines						
	Exhaust hose						
	- Coolant hoses						
	Drain and refill engine fluids						
	Remove and install						
	Soundshield (as needed)						
	Governor actuator						
	 Test run unit 						
05-1AC	Fuel Pump, Electrical – Replace	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Fuel lines (as needed)						
	 Fuel filter assembly 						
	Fuel pump						
	 Test run unit 						



Standard Repair Times		Removed From Chassis	;	Service		nassis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
05–102	Pump, Injection – Replace	-	-	2.2	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Governor actuator 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	Fuel injection pump						
	 Test run unit 						





Group 06 – Injectors and Fuel Lines

	Page
Injectors	46
Replace	46



Standard Repair Times		Removed From Chassis	;	In-Chassis Service Accessibility Codes			Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
06–149	Injectors – Replace	_	_	2.5	_	_	_
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	- Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Fuel lines (as needed)						
	 Fuel injection supply and return lines 						
	Glowplugs						
	 Injectors and seals 						
	 Test run unit 						



Group 07 – Lubricating Oil System

	Page
Oil Pan and Gasket	
Replace	. 48
Oil Pump	48
Replace	. 48
Oil Pickup Tube and Strainer	49
Replace	. 49
Oil Filter and Fluid	
Replace	. 49
Oil Pressure Relief Valve	50
Inspect and Replace	. 50



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
07–109	Oil Pan and Gasket – Replace	-	-	3.0	-	-	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	Exhaust hose								
	Coolant hoses								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	Engine mounts								
	 Heat exchanger 								
	 Oil pan and gasket 								
	 Test run unit 								
07–113	Oil Pump - Replace	-	-	4.5	-	-	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	 Exhaust hose 								
	Coolant hoses								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	 Coolant pump drive belt 								
	 Coolant pumps 								
	 Coolant hoses 								
	 Governor actuator 								
	 Crankshaft pulley 								
	 Gearcase cover and gasket 								
	 Oil pump drive gear 								
	 Oil pump and gasket 								



Standard Repair Times		Removed From Chassis	om The Orlassis						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
	(continued from previous page)								
07–113	Oil Pump – Replace	-	-	4.5	-	-	-		
	Test run unit								
07–114	Oil Pickup Tube and Strainer - Replace	-	-	3.25	-	-	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	Exhaust hose								
	Coolant hoses								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	 Engine mounts 								
	 Heat exchanger 								
	 Oil pan and gasket 								
	 Oil pickup tube and strainer 								
	 Test run unit 								
07–301	Oil Filter and Fluid – Replace	_	-	0.5	-	_	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	 Exhaust hose 								
	 Coolant hoses 								
	 Drain and refill engine fluids 								
	 Remove and install 								
	Oil filter								
	 Test run unit 								



Sta	ndard Repair Times	Removed From Chassis	;	nassis ssibility Codes			
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
07–410	Oil Pressure Relief Valve – Inspect and Replace	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	Oil filter						
	 Valve assembly 						
	 Clean and visually inspect or replace 						
	 Bore, spring, ball, and seat 						
	 Test run unit 						



Group 08 – Cooling System

	Page
Thermostat	52 52
Heat Exchanger	52 52
Water Pipe	53 53
Belt Guard	53 53
Raw Water Pump	53 53
Coolant Pump	54 54
Drive Belt, Water Pump	55 55



Standard Repair Times		Removed From Chassis	111-01103515						
							<u>Special</u>		
	Procedure Number and Description	R	Α	В	С	D	S		
08–104	Thermostat – Replace	_	_	1.5	_	_	_		
00 101	Includes:			1.0					
	Disconnect and connect								
	Battery cables								
	Engine wiring harness (as needed)								
	– Fuel lines								
	Exhaust hose								
	Coolant hoses								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	Coolant hoses								
	 Thermostat cover and gasket 								
	Thermostat								
	 Test run unit 								
08–119	Heat Exchanger – Remove And Install	-	-	3.0	-	-	-		
	Includes:								
	 Disconnect and connect 								
	 Battery cables 								
	 Engine wiring harness (as needed) 								
	Fuel lines								
	Exhaust hose								
	 Coolant hoses 								
	 Drain and refill engine fluids 								
	 Remove and install 								
	 Soundshield (as needed) 								
	 Coolant hoses 								
	 Heat exchanger 								
	 Test run unit 								



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
08–124	Water Pipe - Remove And Install	-	-	3.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust hose 							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Raw water pipe 							
	Test run unit							
08–142	Belt Guard - Replace	-	-	0.3	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	 Exhaust hose 							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Belt guard 							
	Test run unit							
08–207	Raw Water Pump - Replace / Rebuild	-	-	1.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	- Fuel lines							
	Exhaust hose							
	Coolant hoses							



Sta	Standard Repair Times		In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
08–207	Raw Water Pump - Replace / Rebuild	-	-	1.0	-	-	-	
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Raw water pump 							
	 Clean and visually inspect or replace 							
	Pump housing							
	- Replace							
	 Cover and gasket 							
	Impeller							
	- Seal							
	 Test run unit 							
08-209	Coolant Pump - Replace / Rebuild	-	-	2.5	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Pump drive belt 							
	 Coolant pump 							
	Impeller							
	 Seal assembly 							
	 Shaft assembly 							
	 Pulley flange 							
	Pump gasket							
	Inspect pump housing							
	Adjust belt tension							
	Test run unit							



Standard Repair Times		Removed From Chassis	From One in America in it.					
							<u>Special</u>	
Procedure Number ar	d Description	R	Α	В	С	D	S	
(continued from previou	s page)							
08-302 Drive Belt, Water Pump	Adjust / Replace	-	-	1.0	-	-	-	
Includes:								
 Disconnect and cor 	nect							
 Battery cables 								
 Engine wiring har 	rness (as needed)							
Fuel lines								
 Exhaust hose 								
 Coolant hoses 								
 Drain and refill engi 	ne fluids							
 Remove and install 								
 Soundshield (as 	needed)							
 Pump drive belt 								
 Adjust belt tension 								
 Test run unit 								





Group 10 – Intake Air System

	rage
Air Intake Silencer Remove and Install	58 58
Intake Manifold	58 58



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
10-1AA	Air Intake Silencer – Remove and Install Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses	-	-	0.5	-	-	-	
	 Drain and refill engine fluids Remove and install Soundshield (as needed) Intake silencer Test run unit 							
10–129	Intake Manifold – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses - Drain and refill engine fluids - Remove and install - Soundshield (as needed) - Intake silencer - Intake manifold - Test run unit	-	-	1.0	-	-	-	



Group 11 – Exhaust System

	Page
Exhaust Manifold	
Remove and Install	60
Exhaust Mixer	
Remove and Install	60



	Procedure Number and Description	R			In-Chassis Service Accessibility Codes					
	Procedure Number and Description	R					<u>Special</u>			
11–105		- ' '	Α	В	С	D	S			
	Exhaust Manifold – Remove and Install	_	-	1.5	-	-	-			
	Includes:									
	 Disconnect and connect 									
	 Battery cables 									
	Engine wiring harness (as needed)									
	- Fuel lines									
	Exhaust hose									
	 Coolant hoses 									
	 Drain and refill engine fluids 									
	Remove and install									
	 Soundshield (as needed) 									
	Coolant hoses									
	 Pump drive belt 									
	 DC charge alternator 									
	 Exhaust manifold and gasket 									
	 Exhaust mixer and gasket 									
	Test run unit									
11–110	Exhaust Mixer – Remove and Install	-	-	1.0	-	-	-			
	Includes:									
	 Disconnect and connect 									
	 Battery cables 									
	 Engine wiring harness (as needed) 									
	- Fuel lines									
	Exhaust hose									
	 Coolant hoses 									
	 Drain and refill engine fluids 									
	 Remove and install 									
	 Soundshield (as needed) 									
	Coolant hoses									
	Pump drive belt									
	 DC charge alternator 									
	 Exhaust mixer and gasket 									
	 Exhaust temperature switch 									
	Test run unit									



Group 13 – Electrical Equipment

	Page
Alternator	62
Replace	. 62
Starter Motor	62
Replace	. 62
Glow Plugs	63
Replace	. 63



Sta	Standard Repair Times		In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
13–101	Alternator – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses - Drain and refill engine fluids - Remove and install - Soundshield (as needed) - Pump drive belt - DC charge alternator	-	-	1.7	-	-	-	
13–104	 Test run unit Starter Motor - Replace Includes: Disconnect and connect Battery cables Engine wiring harness (as needed) Fuel lines Exhaust hose Coolant hoses Drain and refill engine fluids Remove and install Soundshield (as needed) Starter Test run unit 	-	-	1.0	-	-	-	



Standard Repair Times		Removed From Chassis	From On the American In-Criassis					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
13–114	Glow Plugs – Replace	-	-	1.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	Coolant hoses							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Glow plugs							
	Test run unit							





Group 16 – Mounting Adaptations

	Page
Flywheel	66
Replace	66
Flywheel Housing	
Replace	66



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							Special	
	Procedure Number and Description	R	Α	В	С	D	S	
16–103	Flywheel – Replace	-	-	5.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Starter							
	 Generator control assembly 							
	 Generator assembly 							
	Flywheel							
	Test run unit							
16–108	Flywheel Housing – Replace	-	-	6.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	Starter							
	 Generator control assembly 							
	 Generator assembly 							
	- Flywheel							
	Flywheel housing							
	- Test run unit							
	root run unit							



Group 17 – Miscellaneous

	Page
Exhaust Tube	
Vibration Isolators	68
Sound Shield	
Muffler, Aqualift	69



Sta	ndard Repair Times	Removed From Chassis	,	Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
17 –1AA	Exhaust Tube - Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses - Drain and refill engine fluids - Remove and install - Soundshield (as needed) - Exhaust tube	-	-	1.0	-	-	
17-1AB	 Test run unit Vibration Isolators - Replace Includes: Disconnect and connect Battery cables Engine wiring harness (as needed) Fuel lines Exhaust hose Coolant hoses Drain and refill engine fluids Remove and install Soundshield (as needed) Drip tray Vibration isolators Test run unit 	-	-	2.0	-	-	-



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
17–1AC	Sound Shield – Replace	-	-	1.7	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	Coolant hoses						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Sound shield 						
	 Test run unit 						
17–131	Muffler, Aqualift – Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	– Muffler						
	 Test run unit 						





Group 21 – Generator Equipment

	Page
Main Circuit Breaker (AC)	. 72
Replace	. 72
Oil Pressure Sender	. 72
Replace	. 72
Gauge	. 73
Replace	. 73
Temperature Sender	. 73
Temperature Sender	. 73
Genset	. 73
Test with Load Bank	



Sta	ndard Repair Times	Removed From Chassis	;	Service		nassis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
21–102	Main Circuit Breaker (AC) – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses - Drain and refill engine fluids - Remove and install - Soundshield (as needed) - Circuit breaker	-	-	0.7	-	-	-
21–105	 Test run unit Oil Pressure Sender – Replace Includes: Disconnect and connect Battery cables Engine wiring harness (as needed) Fuel lines Exhaust hose Coolant hoses Drain and refill engine fluids Remove and install Soundshield (as needed) Sender Test run unit 	-	-	0.5	-	-	-



Standard Repair Times		Removed From Chassis	On the Annual little Only				
							Special
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
21–313	Gauge – Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Fuel lines 						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	- Gauge						
	 Test run unit 						
21–315	Temperature Sender – Replace	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Sender						
	 Test run unit 						
21–701	Genset – Test with Load Bank	-	-	1.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Engine wiring harness (as needed) 						
	Load bank						





Group 25 – Generator

	Page
Main Rotor	76
Replace	76
Main Stator	76
Replace	76
Exciter Rotor	
Replace	77
Exciter Stator	
Replace	77
Generator Bearing	
Replace	78
Rotating Diode Assemblies	78
Replace	78



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
	Procedure Number and Description	R	Α	В	С	D	<u>Special</u> S	
25-1AA	Main Rotor – Replace Includes: - Disconnect and connect - Battery cables - Engine wiring harness (as needed) - Fuel lines - Exhaust hose - Coolant hoses - Drain and refill engine fluids - Remove and install - Soundshield (as needed) - Generator mounts - End bell / bearing carrier - Main stator - Main rotor assembly		-	5.0	-		-	
25-1AB	 Test run unit Main Stator - Replace Includes: Disconnect and connect Battery cables Engine wiring harness (as needed) Fuel lines Exhaust hose Coolant hoses Drain and refill engine fluids Remove and install Soundshield (as needed) Generator mounts End bell / bearing carrier Main stator Test run unit 	-	-	5.0	-	-	-	



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
	(continued from previous page)							
25-1AE	Exciter Rotor – Replace	-	-	5.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	 Fuel lines 							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Generator mounts 							
	 End bell / bearing carrier 							
	 Main stator 							
	 Main rotor assembly 							
	Test run unit							
25-1AF	Exciter Stator - Replace	-	-	3.0	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Generator mounts 							
	 End bell / bearing carrier 							
	Exciter stator							
	Test run unit							



Sta	ndard Repair Times	Removed From Chassis	;	Service		assis ssibility	Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
25-3AC	Generator Bearing – Replace	-	-	4.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator mounts 						
	 End bell / bearing carrier 						
	 Generator bearing 						
	Test run unit						
25-3AD	Rotating Diode Assemblies - Replace	-	-	4.0	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Generator mounts 						
	 End bell / bearing carrier 						
	 Rotating diode assemblies 						
	Test run unit						



Group 26 – Generator Control Components

	Page
DC Wire Harness	80
AC Control Box	80 80
Digital Display	80
PCB Control Board	81 81
Circuit Breaker (DC)	81 81
Start / Stop Switch	82 82
Hourmeter	82 82
Relay	83
PCB Network Interface Module (NIM)	83



Sta	ndard Repair Times	Removed From Chassis	In-Chassis Service Accessibility Codes					
							<u>Special</u>	
	Procedure Number and Description	R	Α	В	С	D	S	
26-1AB	DC Wire Harness – Replace	-	-	1.7	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Electrical wiring 							
	 Test run unit 							
26-1AC	AC Control Box – Replace	-	-	1.5	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							
	 Engine wiring harness (as needed) 							
	Fuel lines							
	Exhaust hose							
	 Coolant hoses 							
	 Drain and refill engine fluids 							
	 Remove and install 							
	 Soundshield (as needed) 							
	 Control box cover 							
	Control box							
	 Ground strap 							
	 Transfer control parts to new box 							
	Test run unit							
26-1AH	Digital Display – Remove and Install	-	-	0.3	-	-	-	
	Includes:							
	 Disconnect and connect 							
	 Battery cables 							



Sta	ndard Repair Times	Removed From Chassis	;	Service	In-Ch Acces		Codes
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
26-1AH	Digital Display – Remove and Install	-	-	0.3	-	-	-
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	Digital dsiplay						
	 Test run unit 						
26-3AB	PCB Control Board – Replace	-	-	1.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Control board 						
	 Test run unit 						
26-3AE	Circuit Breaker (DC) – Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes				
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
26-3AE	Circuit Breaker (DC) – Replace	-	-	0.5	-	-	-
	 Remove and install 						
	 Soundshield (as needed) 						
	 Control box cover 						
	Circuit breaker						
	 Test run unit 						
26-3AJ	Start / Stop Switch - Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Control box cover 						
	Start / Stop switch						
	Test run unit						
26-3AK	Hourmeter – Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Control box cover 						
	Hourmeter						
	 Test run unit 						



Standard Repair Times		Removed From Chassis	In-Chassis Service Accessibility Codes				
							<u>Special</u>
	Procedure Number and Description	R	Α	В	С	D	S
	(continued from previous page)						
26-3AL	Relay - Replace	-	-	0.3	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	 Fuel lines 						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Control box cover 						
	- Relay						
	Test run unit						
26-668	PCB Network Interface Module (NIM) - Replace	-	-	0.5	-	-	-
	Includes:						
	 Disconnect and connect 						
	 Battery cables 						
	 Engine wiring harness (as needed) 						
	Fuel lines						
	Exhaust hose						
	 Coolant hoses 						
	 Drain and refill engine fluids 						
	 Remove and install 						
	 Soundshield (as needed) 						
	 Network interface module 						
	 Test run unit 						





Index

A

AC Control Box, Replace, 80

Administrative Time
Open/Close Repair Order (Road), 3
Open/Close Repair Order (Shop), 3

Alternator, Replace, 62

B

Belt Guard, Replace, 53 Breather, Service, 38

C

Camshaft, Fuel, Replace, 24
Camshaft, Valve, Replace, 24
Circuit Breaker (DC), Replace, 81
Connecting Rod, Remove And Install, 25
Connecting Rod Bearings, Replace, 26
Control Board, Replace, 81
Coolant Pump, Replace / Rebuild, 54
Crankshaft, Remove And Install, 27
Crankshaft Seal, Front, Replace, 30
Crankshaft Seal, Rear, Replace, 30
Cylinder Head Gasket, Replace, 34

D

DC Wire Harness, Replace, 80
Digital Display, Remove and Install, 80
Drive Belt, Water Pump, Adjust / Replace, 55

E

Engine, Rebuild, 19
Exciter Rotor, Replace, 77
Exciter Stator, Replace, 77
Exhaust Manifold, Remove and Install, 60

Exhaust Mixer, Remove and Install, 60 Exhaust Tube, Replace, 68

F

Flywheel, Replace, 66 Flywheel Housing, Replace, 66 Fuel Pump, Electrical, Replace, 42

G

Gauge, Replace, 73
Gear Case Cover, Remove And Install, 28
Gear, Crankshaft, Remove And Install, 28
Generator Bearing, Replace, 78
Genset, Test with Load Bank, 73
Genset (Above Deck), Remove and Install, 18
Genset (Below Deck), Remove and Install, 18
Genset Engine Assembly, Replace, 20
Glow Plugs, Replace, 63
Governor Actuator, Replace, 42

Н

Heat Exchanger, Remove and Install, 52 Hourmeter, Replace, 82

I

Injectors, Replace, 46 Intake Manifold, Replace, 58

M

Main Circuit Breaker, Replace, 72 Main Rotor, Replace, 76 Main Stator, Replace, 76 Muffler, Aqualift, Replace, 69

N

Network Interface Module (NIM), Replace, 83



0

Oil Filter and Fluid, Replace, 49

Oil Pan and Gasket, Replace, 48

Oil Pickup Tube and Strainer, Replace, 49

Oil Pressure Relief Valve, Inspect and Replace, 50

Oil Pressure Sender, Replace, 72

Oil Pump, Replace, 48

P

PCB Control Board, Replace, 81

PCB Network Interface Module (NIM), Replace, 83

Piston, Remove and Install, 29

Pump, Injection, Replace, 43

R

Raw Water Pump, Replace / Rebuild, 53

Relay, Replace, 83

Rotating Diode Assemblies, Replace, 78

S

Sound Shield, Replace, 69 Start / Stop Switch, Replace, 82 Starter Motor, Replace, 62

Т

Temperature Sender, Replace, 73

Thermostat, Replace, 52

Troubleshoot

Coolant Loss, 6

Engine Oil Leak, 6

Engine Will Not Crank, 3

Excess White Smoke at Start-Up (Cold), 8

Excess White Smoke at Start-Up (Warm), 7

Excessive Smoke Under Load (Overload Condition), 7

Fault Code 1 (High Engine Temperature), 8

Fault Code 12 (Overvoltage), 11

Fault Code 13 (Undervoltage), 11

Fault Code 14 (Overfrequency), 12

Fault Code 15 (Underfrequency), 12

Fault Code 17 (Overprime), 12

Fault Code 2 (Low Oil Pressure), 9

Fault Code 22 (Actuator Overload), 13

Fault Code 23 (Faulty Oil Pressure Sender), 13

Fault Code 24 (Faulty Temperature Sender), 14

Fault Code 27 (Loss of Voltage Sense), 15

Fault Code 29 (High Battery Voltage), 15

Fault Code 35 (Control Card EE Checksum), 15

Fault Code 36 (Engine Stopped), 16

Fault Code 37 (Invalid Set Configuration), 16

Fault Code 38 (Field Overflow), 16

Fault Code 4 (Overcrank), 10

Fault Code 41 (Grounded Rotor), 17

Fault Code 42 (Control Card ROM), 17

Fault Code 43 (Control Card RAM), 17

Fault Code 48 (Control Card Field Voltage

Sense), 17

Fault Code 58 (High Exhaust Temp), 18

Fault Code 61 (Emergency Shutdown), 18

Fault Code 7 (Loss of Raw Water Flow), 10

Genset Cranks But Will Not Start, 6

Genset Starts But Stops After Switch Releases,

4

Genset Unstable (Hunts), 7

High/Low AC Output, 4

No AC Output Voltage, 5

Unbalanced Output Voltage, 5

Unstable Voltage with Stable Engine, 5

V

Valve Guides, Replace, 34

Valve Tappets, Remove and Install, 40

Valves

Adjust, 38

Replace, 36

Vibration Isolators, Replace, 68

W

Water Pipe, Remove and Install, 53



Request for SRT Review

Distributor/De	ealer Data						
Distributor/Dealer		Phone No.					
Address							
City		S	State	Zip Code			
Country							
My experienc	e has indicated th	ne following rep	pair procedures	require mo	ore time:		
Procedure Da	ata						
SRT Number	Procedure	Discription	Published	time Hrs.	Suggested time Hrs.		
			To	tal Hours			
Generator Se	t Model						
Transfer Swit							
Repair Date							
Technician N	ame						
100111111111111111111111111111111111111	<u></u>						
Describe how repair was performed:							
Signature			Title				
Mail to: On Sei 140 Mir	an Corporation rvice Department 00 73rd Avenue NI nneapolis, MN 554	E 132					





Cummins Power Generation 1400 73rd Avenue N.E. Minneapolis, MN 55432 763-574-5000 Fax: 763-528-7229

